

MAXWELL'S EQUATIONS WITH SCALAR IMPEDANCE: INVERSE PROBLEMS WITH DATA GIVEN ON A PART OF THE BOUNDARY

Yaroslav Kurylev
Loughborough University
Department of Mathematical Sciences
Leicestershire LE11 3TU, UK

Matti Lassas
Helsinki University of Technology
Institute of Mathematics
PO Box 1100, 02015 TKK, Finland

Erkki Somersalo
Helsinki University of Technology
Institute of Mathematics
PO Box 1100, 02015 TKK, Finland

Abstract: We study Maxwell's equations in time domain in an anisotropic medium. The goal of the paper is to solve an inverse boundary value problem for anisotropies characterized by scalar impedance α . This means that the material is conformal, i.e., the electric permittivity ϵ and magnetic permeability μ are tensors satisfying $\mu = \alpha^2 \epsilon$. This condition is equivalent to a single propagation speed of waves with different polarizations which uniquely defines an underlying Riemannian structure. The analysis is based on an invariant formulation of the system of electrodynamics as a Dirac type first order system on a Riemannian 3-manifold with an additional structure of the wave impedance, (M, g, α) , where g is the travel-time metric. We study the properties of this system in the first part of the paper. In the second part we consider the inverse problem, that is, the determination of (M, g, α) from measurements done only on an open part of the boundary and on a finite time interval. As an application, in the isotropic case with $M \subset \mathbb{R}^3$, we prove that the boundary data given only on an open part of the boundary determine uniquely the domain M and the coefficients ϵ and μ .

Keywords: Maxwell's equations, manifolds, inverse problems.

INTRODUCTION

In this paper we study direct and inverse boundary value problems for Maxwell's equations on Euclidean domains in $\mathbb{R}^3$ and on compact manifolds. In a bounded smooth domain $M^{\text{int}} \subset \mathbb{R}^3$, Maxwell's equations for the electric and magnetic fields E and H and the associated electric displacement D and magnetic flux density B are

$$\begin{aligned} (1) \quad & \text{curl } E(x, t) = -B_t(x, t), \quad (\text{Maxwell-Faraday}), \quad \text{div } B(x, t) = 0, \\ (2) \quad & \text{curl } H(x, t) = D_t(x, t), \quad (\text{Maxwell-Ampère}), \quad \text{div } D(x, t) = 0. \end{aligned}$$

Under the assumption of non-dispersive, linear and non-chiral medium, these are augmented with the constitutive relations

$$(3) \quad D(x, t) = \epsilon(x)E(x, t), \quad B(x, t) = \mu(x)H(x, t).$$

Here electric permittivity ϵ and magnetic permeability μ are smooth 3×3 time-independent positive matrices.

The present work consists of two parts. In the first part, we pursue further the invariant formulation of Maxwell's equations (1)–(3) for certain anisotropic materials, characterized by a *scalar wave impedance*. This means that the material is conformal in the sense that

$$(4) \quad \mu = \alpha^2 \epsilon,$$

where α is a positive scalar function. Physically, the condition of a scalar wave impedance is tantamount to a single propagation speed of waves with different polarizations and, without it, the wave propagation gives rise to several generally non-Riemannian metrics, see e.g. [23]. Therefore, we consider direct (and inverse) problems for the most general subclass of Maxwell's equations which is distinguished by the fact that electromagnetic fields with different polarization propagate with the same velocity which, of course, may depend on the propagation direction. The scalar wave impedance is encountered in many physical situations. For instance, in a curved spacetime with coordinates $(x, t) \in \mathbb{R}^3 \times \mathbb{R}$ and a “time-independent” metric $ds^2 = g_{jk}(x)dx^jdx^k - dt^2$, Maxwell's equations with scalar permittivity and permeability correspond in the coordinate invariant form to Maxwell's equations (1)–(3) with scalar wave impedance, see [17, Sec. 14.1.c] or [38, Sec. 90]. Clearly, all isotropic media, i.e. with scalar ϵ and μ have scalar wave impedance.

The invariant approach leads us to formulate Maxwell's equations on 3-manifolds as a first order Dirac type system. From the operator theoretic point of view, this formulation is based on an elliptization procedure by extending Maxwell's equations to the bundle of exterior differential forms over the manifold. This is a generalization of the elliptization of Birman and Solomyak and Picard (see [2, 53]).

In the second part of the work, we consider the inverse boundary value problem for Maxwell's equations with scalar wave impedance. In physical terms, the goal is to determine the material parameter tensors ϵ and μ in a bounded domain from field observations at the boundary or a part of the boundary of that domain.

In the invariant approach to Maxwell's equations, the domain M is considered as a 3-manifold and the vector fields E , H , D and B as differential forms. This alternative formulation has several advantages both from the theoretical and practical points of view. First, the invariance of the system and the boundary measurements with respect to diffeomorphisms of M that preserve the part of the boundary where these measurement are done is essential for the inverse problem. It is possible to prove unique identifiability in the invariant formulation and then use this result to completely characterize group of transformations between indistinguishable parameters ϵ and μ in the case $M \subset \mathbb{R}^3$. In particular, when ϵ and μ are scalar functions, this result implies uniqueness of the determination of ϵ , μ , and M from data on a part of boundary.

Second, the formulation of electrodynamics in terms of differential forms reflects the way in which these fields are actually observed. For instance, flux quantities are expressed as 2-forms while field quantities that correspond to forces are naturally written as 1-forms. This point of view has been adopted in modern physics, at least in the free space, see e.g. [17], as well as in applications where the numerical treatment of the equations is done using the Whitney elements. An extensive treatment of this topic can be found in [11, 12]. For the original reference concerning the Whitney elements, see [64].

As inverse problems of electrodynamics have a great significance in physics and applications, they have been studied starting from the 30's, see e.g. [39, 56], where the one-dimensional case was considered. However, results concerning the multi-dimensional inverse problems in electrodynamics are relatively recent. The first breakthrough achieved in [58, 14, 50, 51] was based on the use of complex geometrical optics. These papers were devoted to the identifiability of isotropic material parameters ϵ and μ from the fixed-frequency data collected on ∂M , namely, the stationary admittance map (for the definition of the time-dependent admittance map see Definition 1.8 in section 1.3.) Under some mild geometric assumptions it was shown there that these data determine isotropic ϵ and μ and also isotropic conductivity, σ , uniquely. These works were based on the ideas previously developed in [61, 46, 47] to tackle the scalar Calderón problem, introduced in [13]. Other approaches to the isotropic inverse problem for Maxwell's equations work directly in the time domain, see [8, 54]. Regarding the case $\sigma = 0$ which is considered in this paper, the result obtained in [54] proves the identifiability of ϵ and μ from the time-dependent data collected on the whole ∂M in the case when M , considered as a Riemannian manifold with metric $dl^2 = \epsilon\mu|dx|^2$, is simple geodesic. Constructions

of [8] make it possible to find the product, $\epsilon\mu$ of unknown parameters ϵ , μ . Moreover, the results of [8] are of a local nature making it possible to find this product only in some collar neighbourhood of ∂M . Time-dependent inverse problem for isotropic Maxwell's equations was also considered in [10] which used a time Fourier transform to reduce the problem to the one in the frequency domain so that to apply the results of [50, 51].

Much less is known in the anisotropic case, where material parameters are matrix valued functions. The case of anisotropic $\epsilon = \mu$ was considered in [6] where it was shown that the time-dependent admittance map known on ∂M makes it possible to recover $\epsilon = \mu$ locally, i.e. in some collar neighbourhood of ∂M . In spite of very little knowledge, it is, however, clear from the study of scalar anisotropic problems that, instead of uniqueness, one obtains uniqueness only up to a group of transformations, involving proper coordinate changes, see e.g. [45, 59, 7, 29, 24, 44, 43]. A similar result for Maxwell's equations was conjectured in [60], based on the analysis of the linearized inverse problem. Therefore, it is natural to split the study of this problem into two steps. First, to formulate and solve the corresponding coordinate-invariant inverse problem, i.e., an inverse problem on a manifold. Second, to analyse the properties resulting from an embedding of the manifold into $\mathbb{R}^3$. For a systematic development of this approach, see [25].

In recent years, inverse problems with data on a part of the boundary have attracted much interest, see [19, 24, 28, 21, 44]. Part of the motivation come from the physical setting when only a part of the boundary is accessible. However, as far as we know, there are currently no results on identifiability of the shape of the domain M and/or the material parameters ϵ , μ on it from inverse data collected on an arbitrary open subset, $\Gamma \subset \partial M$.

A fruitful approach to scalar inverse problems, including those with data on a part of the boundary, turned out to be the boundary control method, originated in [5] for the isotropic acoustic wave equation. In the anisotropic context, it has been developed for the Laplacian on Riemannian manifolds [7] and for general anisotropic self-adjoint [30, 31]) and certain non-selfadjoint inverse problems [33].

The current article pursues the study of inverse problems for Maxwell's equations significantly further dealing with the global reconstruction of the shape of the domain or, more general, 3-manifold M , metric tensor g and scalar wave impedance α , the latter two being equivalent to the reconstruction of ϵ and μ . Being based on the boundary control, the method developed here combines ideas of the articles [34] and [35] with those of [50] and [51]. What is more, to be able to study anisotropic Maxwell's equations, we introduce two essential new ideas. First, we characterize the subspaces controlled from the boundary *by duality*, thus avoiding the difficulties arising from the complicated topology of the domains of influence but still providing necessary information about the structure of achievable sets, see e.g. Theorem 1.15

in section 1.5. This makes our approach much different from that in [6, 8] also based on the boundary control method. Indeed, the method of [6, 8] requires local controllability in the domains of influence which is no more valid for large times, e.g. [9] thus making constructions of [6, 8] inappropriate outside a collar neighbourhood of ∂M . Second, we develop a *method of focused waves* which enables us to recover pointwise values of electromagnetic waves on the manifold and, therefore, reconstruct not only the metric g , as in [8], but also the impedance α .

The main results of this paper can be summarized as follows.

- (1) The knowledge of the complete dynamical boundary data over a sufficiently large finite period of time determines uniquely the compact manifold endowed with the travel time metric as well as the scalar wave impedance (Theorem 2.1). This is valid also when measurements are made on a part of the boundary (Theorem 2.14). The necessary time of observation is double of the time required to fill the manifold from the observed part of the boundary.
- (2) For the corresponding anisotropic inverse boundary value problem with scalar wave impedance for bounded domains in $\mathbb{R}^3$, the non-uniqueness is completely characterized by describing the class of possible transformations between material tensors that are indistinguishable from the observed part of the boundary (Theorem 2.18).
- (3) For the corresponding isotropic inverse boundary value problem for bounded domains in $\mathbb{R}^3$, the shape of the domain and the material parameters inside it are uniquely determined from measurements done on a part of the boundary (Theorem 2.20).

Some of the results of the paper have been announced in [36, 37].

1. MAXWELL'S EQUATIONS ON A MANIFOLD

This chapter is devoted to Maxwell's equations on a compact oriented 3-manifold with boundary. We concentrate on the properties of these equations important for the inverse problem considered in Chapter 2.

We start with the formulation of Maxwell's equations for 1- and 2-forms. These equations are augmented to the complete Maxwell system on the full bundle of exterior differential forms over a 3-dimensional Riemannian manifold. This allows us to define and analyze properties of an elliptic operator related to Maxwell's equations and to study the corresponding initial boundary value problem. Crucial results of Sections 1.3 and 1.4 are the Blagovestchenskii formula, Theorem 1.9, enabling us to evaluate inner products of electromagnetic waves in terms of the admittance map $\mathcal{Z}$, also defined in Section 1.3, and the unique continuation result for Maxwell's equations with Cauchy data on the lateral boundary. Building on these results,

we obtain local and global controllability for electromagnetic waves generated by boundary sources and define, in a usual manner, spaces of generalized sources.

1.1. Invariant definition of Maxwell's equations. To define Maxwell's equations invariantly, consider a smooth compact oriented connected Riemannian 3-manifold M , $\partial M \neq \emptyset$, with a metric g_0 , that we call the background metric. Clearly, in physical applications we take $M \subset \mathbb{R}^3$ with g_0 being the Euclidean metric. Analogously to (1) and (2), Maxwell's equations on the manifold M are equations of the form

$$(5) \quad \operatorname{curl} E(x, t) = -B_t(x, t), \quad \operatorname{div} B(x, t) = 0,$$

$$(6) \quad \operatorname{curl} H(x, t) = D_t(x, t), \quad \operatorname{div} D(x, t) = 0.$$

Here $E, H, D, B \in \Gamma M$, the space of C^∞ -smooth vector fields on M . They are related by the constitutive relations,

$$(7) \quad D(x, t) = \epsilon(x)E(x, t), \quad B(x, t) = \mu(x)H(x, t),$$

where ϵ and μ are C^∞ -smooth positive definite $(1, 1)$ -tensor fields on M . We remind that, for $X \in \Gamma M$,

$$(8) \quad (\operatorname{curl} X)^b = *_0 dX^b, \quad \operatorname{div} X = - *_0 d *_0 X^b.$$

Here, d is the exterior differential, b is the fiberwise duality between 1-forms and vector fields

$$X \in \Gamma M \rightarrow X^b \in \Omega^1 M, \quad X^b(Y) = g_0(X, Y),$$

with $\Omega^1 M$ and, generally, $\Omega^k M$ standing for the bundle of differential k -forms on M . At last $*_0$ is the Hodge operator with respect to metric g_0 , acting fiberwise,

$$*_0 : \Omega^k M \rightarrow \Omega^{3-k} M.$$

Throughout the paper, we assume that the wave impedance is scalar, i.e.,

$$(9) \quad \mu = \alpha^2 \epsilon,$$

where $\alpha = \alpha(x)$ is a positive scalar function. This allows us to introduce a new metric, g on M . Considering it as a quadratic form on differential 1-forms, we have

$$(10) \quad g(X^b, Y^b) = \frac{1}{\det z} g_0(X^b, zY^b), \quad g^{ij} = \frac{1}{\det z} g_0^{ik} z_k^j, \quad z = \alpha \epsilon = \frac{1}{\alpha} \mu,$$

As we see later, this metric is responsible for the velocity of electromagnetic wave propagation and we call it the *travel-time metric*.

Introduce the differential 1- and 2-forms, ω^1, ν^1 and ω^2, ν^2 ,

$$(11) \quad \omega^1 = E^b, \quad \nu^1 = \alpha H^b, \quad \omega^2 = *_0 B^b, \quad \nu^2 = *_0 \alpha D^b.$$

Applying the operator $\flat$ to Maxwell's equations (5)-(6), we rewrite them in terms of $\omega^1, \nu^1, \omega^2, \nu^2$,

$$(12) \quad \begin{aligned} d\omega^1 &= -\omega_t^2, & d\omega^2 &= 0, \\ d\frac{1}{\alpha}\nu^1 &= \frac{1}{\alpha}\nu_t^2, & d\frac{1}{\alpha}\nu^2 &= 0. \end{aligned}$$

Now, using (10) it is a straightforward matter to check that the constitutive relations (7) assume the form,

$$(13) \quad \nu^2 = *\omega^1, \quad \omega^2 = *\nu^1,$$

where $*$ is the Hodge operator with respect to the travel-time metric, g . Eliminating, by means of (13), $\nu^{1,2}$ from equations (12), we transform (5)-(7) into the system

$$(14) \quad \omega_t^1 = \delta_\alpha \omega^2, \quad \delta_\alpha \omega^1 = 0,$$

$$(15) \quad \omega_t^2 = -d\omega^1, \quad d\omega^2 = 0.$$

Here, $\delta_\alpha : \Omega^k M \rightarrow \Omega^{3-k} M$ is the α -codifferential, given by

$$(16) \quad \delta_\alpha \omega^k = (-1)^k * \alpha d \frac{1}{\alpha} * \omega^k,$$

and $*$ is the Hodge operator in the metric g . These equations are called *Maxwell's equations for forms* on the Riemannian manifold with a scalar wave impedance (M, g, α) .

To extend the above equations to the full bundle of exterior differential forms $\Omega M = \Omega^0 M \times \Omega^1 M \times \Omega^2 M \times \Omega^3 M$, we introduce auxiliary forms, $\omega^0 \in \Omega^0 M$ and $\omega^3 \in \Omega^3 M$, which vanish in the electromagnetic theory, by

$$\omega_t^0 = \delta_\alpha \omega^1, \quad \omega_t^3 = -d\omega^2.$$

Since $\omega^0 = 0$ and $\omega^3 = 0$ in electromagnetics, we can modify equations (14) and (15) to read

$$(17) \quad \omega_t^1 = -d\omega_0 + \delta_\alpha \omega^2, \quad \omega_t^3 = -d\omega^2,$$

$$(18) \quad \omega_t^2 = -d\omega^1 + \delta_\alpha \omega^3, \quad \omega_t^0 = \delta_\alpha \omega^1,$$

or, in the matrix form,

$$(19) \quad \omega_t + \mathcal{M}\omega = 0,$$

where $\omega = (\omega^0, \omega^1, \omega^2, \omega^3) \in \Omega M$, and the operator $\mathcal{M}$ (without prescribing its domain at this point, i.e., defined as a differential expression) is given as

$$(20) \quad \mathcal{M} = \begin{pmatrix} 0 & -\delta_\alpha & 0 & 0 \\ d & 0 & -\delta_\alpha & 0 \\ 0 & d & 0 & -\delta_\alpha \\ 0 & 0 & d & 0 \end{pmatrix}.$$

Equations (19), (20) are called *the complete Maxwell system*.

Note that, identifying ΩM with $\Omega^0 M \oplus \Omega^1 M \oplus \Omega^2 M \oplus \Omega^3 M$, the complete Maxwell operator can be written as

$$(21) \quad \mathcal{M} = d - \delta_\alpha,$$

i.e., it becomes a Dirac type operator on ΩM .

An important property of $\mathcal{M}$ is that

$$\mathcal{M}^2 = -\text{diag}(\Delta_\alpha^0, \Delta_\alpha^1, \Delta_\alpha^2, \Delta_\alpha^3) = -\Delta_\alpha,$$

where the operator Δ_α^k acts on k -forms as

$$(22) \quad \Delta_\alpha^k = d\delta_\alpha + \delta_\alpha d = \Delta_g^k + Q^k(x, D).$$

Here Δ_g^k is the Laplace-Beltrami operator in the metric g and $Q^k(x, D)$ is a first order perturbation. Hence, if ω satisfies equation (19), it satisfies also wave equation

$$(23) \quad (\partial_t^2 + \Delta_\alpha)\omega = (\partial_t - \mathcal{M})(\partial_t + \mathcal{M})\omega = 0.$$

This formula legitimates the notion of the travel time metric and makes clear that in the Maxwell system with scalar impedance, the electromagnetic waves of different polarization propagate with the same speed determined by the metric g .

We end this section with representation of the energy of electric and magnetic fields in terms of the corresponding differential forms, setting

$$\begin{aligned} \mathcal{E}(E) &= \frac{1}{2} \int_M g_0(\epsilon E, E) dV_0 = \frac{1}{2} \int_M \frac{1}{\alpha} \omega^1 \wedge * \omega^1, \\ \mathcal{E}(B) &= \frac{1}{2} \int_M g_0(\mu H, H) dV_0 = \frac{1}{2} \int_M \frac{1}{\alpha} \omega^2 \wedge * \omega^2, \end{aligned}$$

where dV_0 is volume form of (M, g_0) . These formulae serve as a motivation for our definition of inner products in the following section.

1.2. The Maxwell operator. In this section we establish a number of notational conventions and definitions concerning the differential forms used in this paper.

We define the L^2 -inner products for k -forms in $\Omega^k M$ as

$$(\omega^k, \eta^k)_{L^2} = \int_M \frac{1}{\alpha} \omega^k \wedge * \eta^k, \quad \omega^k, \eta^k \in \Omega^k M,$$

and denote by $L^2(\Omega^k M)$ the completion of $\Omega^k M$ in the corresponding norm. We also define

$$\mathbf{L}^2(M) = L^2(\Omega^0 M) \times L^2(\Omega^1 M) \times L^2(\Omega^2 M) \times L^2(\Omega^3 M),$$

with Sobolev spaces $\mathbf{H}^s(M)$, $\mathbf{H}_0^s(M)$, $s \in \mathbb{R}$, given as

$$\mathbf{H}^s(M) = H^s(\Omega^0 M) \times H^s(\Omega^1 M) \times H^s(\Omega^2 M) \times H^s(\Omega^3 M),$$

$$\mathbf{H}_0^s(M) = H_0^s(\Omega^0 M) \times H_0^s(\Omega^1 M) \times H_0^s(\Omega^2 M) \times H_0^s(\Omega^3 M).$$

Here, $H^s(\Omega^k M)$ is the Sobolev space of k -forms and $H_0^s(\Omega^k M)$ is the closure in $H^s(\Omega^k M)$ of the set of k -forms in $\Omega^k M$, which vanish near ∂M .

Clearly, the natural domain of the exterior derivative, d in $L^2(\Omega^k M)$ is

$$H(d, \Omega^k M) = \{\omega^k \in L^2(\Omega^k M) \mid d\omega^k \in L^2(\Omega^{k+1} M)\},$$

and the natural domain of δ_α is

$$H(\delta_\alpha, \Omega^k M) = \{\omega^k \in L^2(\Omega^k M) \mid \delta_\alpha \omega^k \in L^2(\Omega^{k-1} M)\}.$$

In the sequel, we drop the sub-index α from the codifferential.

The operators d and δ are adjoint, i.e. for C_0^∞ -forms ω^k, η^{k+1} ,

$$(d\omega^k, \eta^{k+1})_{L^2} = (\omega^k, \delta\eta^{k+1})_{L^2}.$$

To extend this formula to less regular forms, let us fix some notations. For $\omega^k \in \Omega^k M$, we define its *tangential* and *normal* boundary components on ∂M as

$$\mathbf{t}\omega^k = i^* \omega^k, \quad \mathbf{n}\omega^k = i^*(\alpha^{-1} * \omega^k),$$

respectively, where $i^* : \Omega^k M \rightarrow \Omega^k \partial M$ is the pull-back of the natural imbedding $i : \partial M \rightarrow M$. With these notations, Stokes' formula for forms can be written as

$$(24) \quad (d\omega^k, \eta^{k+1})_{L^2} - (\omega^k, \delta\eta^{k+1})_{L^2} = \langle \mathbf{t}\omega^k, \mathbf{n}\eta^{k+1} \rangle,$$

where, for $\omega^k \in \Omega^k M$ and $\eta^{k+1} \in \Omega^{k+1} M$,

$$\langle \mathbf{t}\omega^k, \mathbf{n}\eta^{k+1} \rangle = \int_{\partial M} \mathbf{t}\omega^k \wedge \mathbf{n}\eta^{k+1}.$$

There are well defined extensions of the boundary trace operators $\mathbf{t}$ and $\mathbf{n}$ to $H(d, \Omega^k M)$ and $H(\delta, \Omega^k M)$. The following result is due to Paquet [52]:

Proposition 1.1. *The operators $\mathbf{t}$ and $\mathbf{n}$ can be extended to continuous surjective maps*

$$\mathbf{t} : H(d, \Omega^k M) \rightarrow H^{-1/2}(d, \Omega^k \partial M), \quad \mathbf{n} : H(\delta, \Omega^{k+1} M) \rightarrow H^{-1/2}(d, \Omega^{2-k} \partial M),$$

where the space $H^{-1/2}(d, \Omega^k \partial M)$ is the space of k -forms ω^k on ∂M satisfying

$$\omega^k \in H^{-1/2}(\Omega^k \partial M), \quad d\omega^k \in H^{-1/2}(\Omega^{k+1} \partial M).$$

Formula (24) is instrumental for characterizing the spaces of forms with vanishing boundary data. Introducing $\mathring{H}(d, \Omega^k M) = \text{Ker}(\mathbf{t})$ and $\mathring{H}(\delta, \Omega^{k+1} M) = \text{Ker}(\mathbf{n})$ and applying Stokes' formula, one can prove in standard way the following lemma.

Lemma 1.2. *The adjoint of the operator*

$$d : L^2(\Omega^k M) \supset H(d, \Omega^k M) \rightarrow L^2(\Omega^{k+1} M)$$

is the operator $\delta : L^2(\Omega^{k+1} M) \supset \mathring{H}(\delta, \Omega^{k+1} M) \rightarrow L^2(\Omega^k M)$ and vice versa. Similarly, the adjoint of

$$\delta : L^2(\Omega^{k+1} M) \supset H(\delta, \Omega^{k+1} M) \rightarrow L^2(\Omega^k M)$$

is the operator $d : L^2(\Omega^k M) \supset \mathring{H}(d, \Omega^k M) \rightarrow L^2(\Omega^{k+1} M)$.

When there is no risk of confusion we will write for brevity $H(d) = H(d, \Omega^k M)$ and similarly, *mutatis mutandis* for the other spaces.

For later reference, we point out that Stokes' formula for the complete Maxwell system can be written as

$$(25) \quad (\eta, \mathcal{M}\omega)_{\mathbf{L}^2} + (\mathcal{M}\eta, \omega)_{\mathbf{L}^2} = \langle \mathbf{t}\omega, \mathbf{n}\eta \rangle + \langle \mathbf{t}\eta, \mathbf{n}\omega \rangle,$$

where $\omega \in \mathbf{H}$ with

$$(26) \quad \mathbf{H} = H(d) \times [H(d) \cap H(\delta)] \times [H(d) \cap H(\delta)] \times H(\delta),$$

$\eta \in \mathbf{H}^1(M)$, $\mathbf{t}\omega = (\mathbf{t}\omega^0, \mathbf{t}\omega^1, \mathbf{t}\omega^2)$, $\mathbf{n}\omega = (\mathbf{n}\omega^3, \mathbf{n}\omega^2, \mathbf{n}\omega^1)$, and

$$\langle \mathbf{t}\omega, \mathbf{n}\eta \rangle = \langle \mathbf{t}\omega^0, \mathbf{n}\eta^1 \rangle + \langle \mathbf{t}\omega^1, \mathbf{n}\eta^2 \rangle + \langle \mathbf{t}\omega^2, \mathbf{n}\eta^3 \rangle.$$

With these notations, we give the following definition of the Maxwell operators with electric boundary condition.

Definition 1.3. *The Maxwell operator with electric boundary condition, $\mathcal{M}_e$, is an operator in $\mathbf{L}^2(M)$, with*

$$\mathcal{D}(\mathcal{M}_e) = \mathring{\mathbf{H}}_{\mathbf{t}} := \mathring{H}(d) \times [\mathring{H}(d) \cap H(\delta)] \times [\mathring{H}(d) \cap H(\delta)] \times H(\delta),$$

and $\mathcal{M}_e\omega$, $\omega \in \mathcal{D}(\mathcal{M}_e)$ is given by the differential expression (20).

In terms of physics, the electric boundary condition is associated with electrically perfectly conducting boundaries, i.e., $n \times E = 0$, $n \cdot B = 0$, where n is the exterior normal vector at the boundary. In terms of differential forms, this means simply that $\mathbf{t}E^b = \mathbf{t}\omega^1 = 0$ and $\mathbf{t} *_0 B^b = \mathbf{t}\omega^2 = 0$. Although not used in the sequel, the Maxwell operator with magnetic boundary condition, $\mathcal{M}_m$, is given by (20) with the domain

$$\mathcal{D}(\mathcal{M}_m) = \mathring{\mathbf{H}}_{\mathbf{n}} := H(d) \times [H(d) \cap \mathring{H}(\delta)] \times [H(d) \cap \mathring{H}(\delta)] \times \mathring{H}(\delta).$$

Consider the intersections of spaces in the definition of $\mathcal{D}(\mathcal{M}_e)$ and $\mathcal{D}(\mathcal{M}_m)$. Let

$$\begin{aligned} \mathring{H}_{\mathbf{t}}^1(\Omega^k M) &= \{\omega^k \in H^1(\Omega^k M) \mid \mathbf{t}\omega^k = 0\}, \\ \mathring{H}_{\mathbf{n}}^1(\Omega^k M) &= \{\omega^k \in H^1(\Omega^k M) \mid \mathbf{n}\omega^k = 0\}. \end{aligned}$$

It is a direct consequence of Gaffney's inequality (see [57]) that

$$\begin{aligned} \mathring{H}(d, \Omega^k M) \cap H(\delta, \Omega^k M) &= \mathring{H}_{\mathbf{t}}^1(\Omega^k M), \\ H(d, \Omega^k M) \cap \mathring{H}(\delta, \Omega^k M) &= \mathring{H}_{\mathbf{n}}^1(\Omega^k M). \end{aligned}$$

The following lemma is a straightforward application of Lemma 1.2 and the classical Hodge-Weyl decomposition [57].

Lemma 1.4. *The electric Maxwell operator has the following properties:*

- (i) *The operator $\mathcal{M}_e$ is skew-adjoint.*
- (ii) *The operator $\mathcal{M}_e$ defines an elliptic differential operator in M^{int} .*
- (iii) $\text{Ker}(\mathcal{M}_e) = \{(0, \omega^1, \omega^2, \omega^3) \in \mathring{\mathbf{H}}_{\mathbf{t}} \mid d\omega^1 = 0, \delta\omega^1 = 0, d\omega^2 = 0, \delta\omega^2 = 0, \delta\omega^3 = 0\}$.
- (iv) $\text{Ran}(\mathcal{M}_e) = L^2(\Omega^0 M) \times (\delta H(\delta, \Omega^2 M) + d\mathring{H}(d, \Omega^0 M)) \times (\delta H(\delta, \Omega^3 M) + d\mathring{H}(d, \Omega^1 M)) \times d\mathring{H}(d, \Omega^2 M)$.

By the skew-adjointness, it is possible to define weak solutions to initial boundary-value problems needed later.

1.3. Initial–boundary value problem. In the sequel, we denote the forms $\omega(x, t)$ by $\omega(t)$ or ω when there is no danger of misunderstanding.

By the *weak solution* to the initial boundary value problem

$$(27) \quad \begin{aligned} \partial_t \omega + \mathcal{M}\omega &= \rho \in L^1_{\text{loc}}(\mathbb{R}, \mathbf{L}^2(M)), \\ \mathbf{t}\omega|_{\partial M \times \mathbb{R}} &= 0, \quad \omega(0) = \omega_0 \in \mathbf{L}^2, \end{aligned}$$

we mean the form $\omega(t) \in C(\mathbb{R}, \mathbf{L}^2(M))$ defined as

$$(28) \quad \omega(t) = \mathcal{U}(t)\omega_0 + \int_0^t \mathcal{U}(t-s)\rho(s)ds,$$

where $\mathcal{U}(t) = \exp(-t\mathcal{M}_e)$ is the unitary operator in $\mathbf{L}^2$ generated by $\mathcal{M}_e$. Similarly, we define weak solutions with initial data at $t = T$, $T \in \mathbb{R}$. Assuming $\rho \in C(\mathbb{R}, \mathbf{L}^2)$, the solution has more regularity, $\omega \in C(\mathbb{R}, \mathbf{L}^2) \cap C^1(\mathbb{R}, \mathbf{H}')$, where $\mathbf{H}'$ denotes the dual of $\mathbf{H}$.

We consider also the normal boundary trace $\mathbf{n}\omega$ of weak solutions. Omitting the details, we note that $\mathbf{n}\omega$ is defined as a limit of smooth solutions approximating the weak one.

The following result gives a sufficient condition for a weak solution of the complete system to be also a solution of Maxwell's equations.

Lemma 1.5. *Assume that the initial data ω_0 is of the form $\omega_0 = (0, \omega_0^1, \omega_0^2, 0)$, where $\delta\omega_0^1 = 0$, $d\omega_0^2 = 0$, and $\rho = 0$. Then the weak solution $\omega(t)$ of the form (28) satisfies also Maxwell's equations (14), (15), i.e., $\omega^0 = 0$ and $\omega^3 = 0$.*

Proof: As seen from (23), $\omega^0(t)$ satisfies the wave equation

$$\Delta_\alpha^0 \omega^0 + \omega_{tt}^0 = 0,$$

with the Dirichlet boundary condition $\mathbf{t}\omega^0 = 0$. The initial data for ω^0 is

$$\omega^0(0) = \omega_0^0 = 0, \quad \omega_t^0(0) = \delta\omega^1|_{t=0} = \delta\omega_0^1 = 0.$$

Hence, $\omega^0(t) = 0$ for all $t \in \mathbb{R}$.

Similarly, $\omega^3(t)$ satisfies the wave equation with the initial data

$$\omega^3(0) = \omega_3^0 = 0, \quad \omega_t^3(0) = -d\omega^2|_{t=0} = -d\omega_0^2 = 0.$$

As for the boundary condition, we observe that

$$\mathbf{t}\delta\omega^3 = \mathbf{t}\omega_t^2 - \mathbf{t}d\omega^1 = \partial_t\mathbf{t}\omega^2 - d\mathbf{t}\omega^1 = 0,$$

i.e., the Neumann data for the function $*\omega^3$ vanish at ∂M . Thus, $\omega^3(t) = 0$. $\square$

Assume that $\omega(t)$ is a smooth solution of the complete system (27). The *complete Cauchy data* of $\omega(t)$ consist of

$$(\mathbf{t}\omega(x, t), \mathbf{n}\omega(x, t)), \quad (x, t) \in \partial M \times \mathbb{R}.$$

The Cauchy data for the solutions $\omega(t)$ of Maxwell's equations have a particular structure. Indeed, by taking the tangential trace of the equation (18), we obtain $\mathbf{t}\omega_t^2 = -d\mathbf{t}\omega^1$. Further, by integrating,

$$(29) \quad \mathbf{t}\omega^2(x, t) = \mathbf{t}\omega^2(x, 0) - \int_0^t d(\mathbf{t}\omega^1(x, t')) dt', \quad x \in \partial M.$$

Similarly, by taking the normal trace of equation (17), we find that $\mathbf{n}\omega_t^1 = d\mathbf{n}\omega^2$, so by integrating

$$(30) \quad \mathbf{n}\omega^1(x, t) = \mathbf{n}\omega^1(x, 0) + \int_0^t d(\mathbf{n}\omega^2(x, t')) dt', \quad x \in \partial M.$$

In this work, we consider mainly the case $\omega(0) = 0$, when the lateral Cauchy data for the original problem of electrodynamics is simply

$$(31) \quad \mathbf{t}\omega = (0, f, -\int_0^t df(t') dt'),$$

$$(32) \quad \mathbf{n}\omega = (0, g, \int_0^t dg(t') dt'),$$

where f and g are functions of t with values in $\Omega^1\partial M$. The following theorem implies that solutions of Maxwell's equations are solutions of the complete Maxwell system and gives sufficient conditions for the converse result.

Theorem 1.6. *If $\omega(t) \in C(\mathbb{R}, \mathbf{H}) \cap C^1(\mathbb{R}, \mathbf{L}^2)$ satisfies the equation*

$$(33) \quad \omega_t + \mathcal{M}\omega = 0, \quad t > 0,$$

with $\omega(0) = 0$, and $\omega^0(t) = 0$, $\omega^3(t) = 0$, then $\mathbf{t}\omega$, $\mathbf{n}\omega$ are of the form (31)–(32).

Conversely, if $\mathbf{t}\omega$, $\mathbf{n}\omega$ are of the form (31)–(32) for $0 \leq t \leq T$, and $\omega(t)$ satisfies (33), with $\omega(0) = 0$, then $\omega(t)$ is a solution of Maxwell's equations, i.e., $\omega^0(t) = 0$, $\omega^3(t) = 0$.

Proof: The first part of the theorem follows from the above considerations if we show that $\omega(t)$ is sufficiently regular. For $\omega^2 \in C(\mathbb{R}, H(\delta, \Omega^2 M))$, by Proposition 1.1, $\mathbf{n}\omega^2 \in C(\mathbb{R}, H^{-1/2}(\Omega^1 \partial M))$ with $d\mathbf{n}\omega^2 \in C(\mathbb{R}, H^{-1/2}(\Omega^2 \partial M))$. As $\delta\omega_t^1(t) = \delta\delta\omega^2(t) = 0$, it holds also that

$$\mathbf{n}\omega_t^1 \in C(\mathbb{R}, H^{-1/2}(\Omega^2 \partial M)),$$

implying (32). To prove (31), we use Maxwell duality: Consider the forms

$$\eta^{3-k} = (-1)^k * \alpha^{-1} \omega^k.$$

Then $\eta = (\eta^0, \eta^1, \eta^2, \eta^3)$ satisfies the complete system dual to the Maxwell system, $\eta_t + \widetilde{\mathcal{M}}\eta = 0$, where $\widetilde{\mathcal{M}}$ is the Maxwell operator with metric g and scalar impedance α^{-1} . Then formula (32) for the solution η implies (31) for ω .

To prove the converse, we observe that the equations,

$$(34) \quad \partial_t \omega^0(t) - \delta \omega^1(t) = 0, \quad \partial_t \omega^1(t) + d\omega^0(t) - \delta \omega^2(t) = 0$$

imply that

$$\omega_{tt}^0(t) + \delta d\omega^0(t) = 0.$$

In addition, $\omega^0(0) = 0$, $\omega_t^0(0) = 0$, and from (31), $\mathbf{t}\omega^0(t) = 0$. Thus, $\omega^0 = 0$ for $0 \leq t \leq T$. By the Maxwell duality described earlier, this implies also that $\omega^3(t) = 0$. $\square$

The following definition, where R is a right inverse to the mapping $\mathbf{t}$, fixes the solutions of the forward problem used in this work.

Definition 1.7. Let $h = (h^0, h^1, h^2) \in C^\infty([0, T], \Omega \partial M)$. The solution $\omega(t)$ of the initial boundary value problem

$$\begin{aligned} \omega_t + \mathcal{M}\omega &= 0, \quad t > 0, \\ \omega(0) &= \omega_0 \in \mathbf{L}^2(M), \quad \mathbf{t}\omega = h, \end{aligned}$$

is given by

$$\omega(t) = Rh(t) + \mathcal{U}(t)\omega_0 - \int_0^t \mathcal{U}(t-s)(\mathcal{M}Rh(s) + Rh_s(s))ds.$$

When $\omega_0 = 0$ and h is a smooth boundary source of the form (31),

$$h = (0, f, -\int_0^t df(t')dt'), \quad f \in C_0^\infty([0, T[, \Omega^1 \partial M),$$

$\omega(t)$ is called the solution of Maxwell's equations in $M \times [0, T]$ with the boundary condition $\mathbf{t}\omega^1 = f$ and the initial condition $\omega(0) = 0$.

To emphasize the dependence of $\omega(t)$ on f above, we write occasionally

$$(35) \quad \omega(t) = \omega^f(t) = (0, (\omega^f)^1, (\omega^f)^2, 0).$$

We note that f could be chosen from a wider class, e.g. from $H^{1/2}(\partial M \times [0, T])$.

We use the notation $\dot{C}^\infty([0, T], \Omega^1 \partial M)$ for the space of C^∞ functions $[0, T] \rightarrow \Omega^1 \partial M$ vanishing near $t = 0$. Theorem 1.6 motivates the following definition.

Definition 1.8. *The admittance map, $\mathcal{Z}^T$ is defined as*

$$\mathcal{Z}^T : \dot{C}^\infty([0, T], \Omega^1 \partial M) \rightarrow \dot{C}^\infty([0, T], \Omega^1 \partial M), \quad \mathbf{t}\omega^1|_{\partial M \times [0, T]} \mapsto \mathbf{n}\omega^2|_{\partial M \times [0, T]},$$

where $\omega(t)$ is the solution of Maxwell's equations in $M \times [0, T]$ with $\omega(0) = 0$.

Note that in the classical terminology of electric and magnetic fields, $\mathcal{Z}^T$ maps the tangential electric field $n \times E|_{\partial M \times [0, T]}$ to the tangential magnetic field $n \times H|_{\partial M \times [0, T]}$.

The following result, which relates the boundary data and the energy of the electromagnetic field, is crucial for boundary control. It is a version of the Blagovestchenskii formula (see [4] for the scalar case).

Theorem 1.9. (1) *For any $T > 0$ and $f, h \in \dot{C}^\infty([0, 2T], \Omega^1 \partial M)$, the knowledge of the admittance map $\mathcal{Z}^{2T}$ allows us to evaluate the inner products*

$$((\omega^f)^j(t), (\omega^h)^j(s))_{L^2}, \quad j = 1, 2, \quad 0 \leq s, t \leq T.$$

(2) *For any $T > 0$ and $f \in \dot{C}^\infty([0, T], \Omega^1(\partial M))$, $\mathcal{Z}^T$ determines the energy of the field ω^f at $t = T$, defined as*

$$\mathcal{E}^T(\omega^f) = \frac{1}{2} \|(\omega^f)^1(T)\|_{L^2}^2 + \frac{1}{2} \|(\omega^f)^2(T)\|_{L^2}^2.$$

Proof: 1. Let $\omega(t) = \omega^f(t)$ and $\eta(s) = \omega^h(s)$ with $F^j(s, t) = (\omega^j(s), \eta^j(t))_{L^2}$, $j = 1, 2$. By (19),

$$\begin{aligned} (36) \quad (\partial_s^2 - \partial_t^2)F^j(s, t) &= (\omega_{ss}^j(s), \eta^j(t))_{L^2} - (\omega^j(s), \eta_{tt}^j(t))_{L^2} \\ &= -((d\delta + \delta d)\omega^j(s), \eta^j(t))_{L^2} + (\omega^j(s), (d\delta + \delta d)\eta^j(t))_{L^2} = b^j(s, t). \end{aligned}$$

We apply Maxwell's equations (14), (15) and the commutation relations,

$$(37) \quad \mathbf{t}d\omega^j = d\mathbf{t}\omega^j, \quad \mathbf{n}\delta\omega^j = \mathbf{t} * d\frac{1}{\alpha} * \omega^j = d\mathbf{t}\frac{1}{\alpha} * \omega^j = d\mathbf{n}\omega^j, \quad j = 1, 2,$$

where d , in the right side is the exterior derivative on ∂M . A straightforward applications of Stokes' formula (24), yields

$$\begin{aligned} b^1(s, t) &= \langle \mathbf{n}\omega_s^2(s), \mathbf{t}\eta^1(t) \rangle - \langle \mathbf{t}\omega^1(s), \mathbf{n}\eta_t^2(t) \rangle, \\ b^2(s, t) &= \langle \mathbf{n}\omega^2(s), \mathbf{t}\eta_t^1(t) \rangle - \langle \mathbf{t}\omega_s^1(s), \mathbf{n}\eta^2(t) \rangle. \end{aligned}$$

As $\mathcal{Z}^{2T}$ determines $b^1(s, t)$ and $b^2(s, t)$ for $t, s < 2T$ and

$$(38) \quad F^j(0, t) = F^j(s, 0) = 0, \quad F_s^j(0, t) = F_t^j(s, 0) = 0,$$

the function $F^j(s, t)$ can be found from the wave equation (36) for $s + t < 2T$.

2. Again, by differentiating and using Maxwell's equations and Stokes' formula, we obtain

$$\partial_t \mathcal{E}^t(\omega^f) = -\langle \mathbf{t}\omega^1(t), \mathbf{n}\omega^2(t) \rangle = -\langle f(t), \mathcal{Z}^T f(t) \rangle.$$

As $\mathcal{E}^0(\omega^f) = 0$, the energy is readily obtained for $t \leq T$. $\square$

1.4. Unique continuation results. For further applications to inverse problems, in this section we consider the unique continuation of the Holmgren-John type for Maxwell's equations. We start with an extension of differential forms outside the manifold M . Let $\Gamma \subset \partial M$ be open and $\widetilde{M}$ be an extension of M across Γ , i.e., $M \subseteq \widetilde{M}$, $\Gamma \subset \widetilde{M}^{\text{int}}$ and $\partial M \setminus \Gamma \subset \partial \widetilde{M}$. Let $\widetilde{g}$, $\widetilde{\alpha}$ be smooth continuations of g and α to $\widetilde{M}$. In this case, we say that the manifold $(\widetilde{M}, \widetilde{g}, \widetilde{\alpha})$ is an *extension of (M, g, α) across Γ* .

Let ω^k be a k -form on M and $\widetilde{\omega}^k$ its extension by zero to $\widetilde{M}$. It follows from Stokes' formula (24) that for $\omega^k \in H(d, \Omega^k M)$ with $\mathbf{t}\omega^k|_{\Gamma} = 0$, we have $\widetilde{\omega}^k \in H(d, \Omega^k \widetilde{M})$. Similarly, if $\omega^k \in H(\delta, \Omega^k M)$ and $\mathbf{n}\omega^k|_{\Gamma} = 0$, then $\widetilde{\omega}^k \in H(\delta, \Omega^k \widetilde{M})$. These yield the following result.

Proposition 1.10. *Let $\omega(t) \in C^1(\mathbb{R}, \mathbf{L}^2) \cap C(\mathbb{R}, \mathbf{H})$ with $\mathbf{t}\omega|_{\Gamma \times [0, T]} = 0$ and $\mathbf{n}\omega|_{\Gamma \times [0, T]} = 0$, be a solution of the complete Maxwell system (19) in $M \times [0, T]$. Let $\widetilde{\omega}$ be its extension by zero across $\Gamma \subset \partial M$. Then $\widetilde{\omega}(t)$ satisfies the complete Maxwell system (19) in $\widetilde{M} \times [0, T]$.*

We are particularly interested in the solutions of Maxwell's equations. The following result extends Proposition 1.10 to this case.

Lemma 1.11. *Let $\omega(t) \in C^1(\mathbb{R}, \mathbf{L}^2) \cap C(\mathbb{R}, \mathbf{H})$ be a solution of Maxwell's equations (14), (15) in $M \times [0, T]$, i.e., $\omega^0(t) = 0$, $\omega^3(t) = 0$. In addition, let $\mathbf{t}\omega^1|_{\Gamma \times [0, T]} = 0$, $\mathbf{n}\omega^2|_{\Gamma \times [0, T]} = 0$, and $\omega(0) = 0$. Then $\widetilde{\omega}(t) \in C^1(\mathbb{R}, \mathbf{L}^2(\widetilde{M})) \cap C(\mathbb{R}, \mathbf{H}(\widetilde{M}))$ is a solution of Maxwell's equations in $\widetilde{M} \times [0, T]$.*

Proof: The above conditions together with Theorem 1.6 imply that

$$\mathbf{t}\omega = (0, \mathbf{t}\omega^1, -\int_0^t d\mathbf{t}\omega^1 dt') = 0, \quad \mathbf{n}\omega = (0, \mathbf{n}\omega^2, \int_0^t d\mathbf{n}\omega^2 dt') = 0$$

in $\Gamma \times [0, T]$. Therefore, by Proposition 1.10, $\widetilde{\omega}(t)$ satisfies (19) in $\widetilde{M} \times [0, T]$. Clearly, also $\widetilde{\omega}^0(t) = 0$, $\widetilde{\omega}^3(t) = 0$ in $\widetilde{M} \times [0, T]$, and $\widetilde{\omega}(0) = 0$. $\square$

When we deal with a general solution to Maxwell's equations (14)–(15), which may not satisfy zero initial conditions, and try to extend them by zero across Γ , the arguments of Lemma 1.11 fail. Indeed, if $\omega(0) \neq 0$, then (30) show that $\mathbf{n}\omega^2 = 0$ is not sufficient for $\mathbf{n}\omega^1 = 0$. However, by differentiating with respect to t , the parasite

term $\mathbf{n}\omega^1(0)$ vanishes. This is the motivation why Theorem 1.12 below deals with the time derivatives of weak solutions.

Let, again, $\Gamma \subset \partial M$ be open and $T > 0$. Denote by $K(\Gamma, T)$ the double cone of influence with the base on the slice $t = T$,

$$K(\Gamma, T) = \{(x, t) \in M \times [0, 2T] \mid \tau(x, \Gamma) < T - |T - t|\}$$

where $\tau(x, y)$ is the distance function on (M, g) (see Figure 1).




FIGURE 1. Left: The double cone of influence. Right: For T large enough, the double cone contains a slice $\{T/2\} \times M$.

We prove the following unique continuation result for the time derivative of the fields.

Theorem 1.12. *Let $\omega(t)$ be a weak solution (28) of the initial boundary value problem (27). Assume that $\omega_0 = (0, \omega_0^1, \omega_0^2, 0)$, $\delta\omega_0^1 = 0$, $d\omega_0^2 = 0$, and $\rho = 0$. If $\mathbf{n}\omega^2 = 0$ on $\Gamma \times]0, 2T[$, then $\omega_t = 0$ in $K(\Gamma, T)$.*

Proof: When $\omega(t) \in C^2(]0, 2T[, \mathbf{L}^2) \cap C^1(]0, 2T[, \mathbf{H})$, then $\eta(t) = \omega_t(t) \in C^1(]0, 2T[, \mathbf{L}^2) \cap C^0(]0, 2T[, \mathbf{H})$ also satisfies Maxwell's equations (14), (15). Let $\widetilde{M}$ be the extension of M across Γ and $\widetilde{\eta}$ be the extension of η by zero. It follows from (29) and (30) that $t\eta^2 = -d\mathbf{t}\omega^1 = 0$ and $\mathbf{n}\eta^1 = d\mathbf{n}\omega^2 = 0$ in $\Gamma \times]0, 2T[$. Therefore, by Proposition 1.10,

$$\widetilde{\eta}(t) \in C^1(]0, 2T[, \mathbf{L}^2(\widetilde{M})) \cap C^0(]0, 2T[, \mathbf{H}(\widetilde{M})),$$

is a solution of the complete system and obviously, also a solution of Maxwell's equations (14), (15) in $\widetilde{M} \times]0, 2T[$.

By the unique continuation for sufficiently smooth solutions (see [16] and Remark 1.13 below), we have that, for any $\sigma > 0$, $\widetilde{\eta} = 0$ in the double cone

$$\{(x, t), x \in \widetilde{M}, t \in \mathbb{R} \mid \widetilde{\tau}(x, \widetilde{M} \setminus M) < T - \sigma - |T - t|\}.$$

Thus, $\eta = 0$ in $K(\Gamma, T)$.

When $\omega(t) \in C^0([0, 2T[, \mathbf{L}^2)$ is a weak solution, we use Friedrich's mollifier in t ,

$$\omega_\sigma = \psi_\sigma * \omega, \quad \psi_\sigma(t) = (1/\sigma)\psi(t/\sigma) \quad \text{for } \sigma > 0,$$

where $\psi \in C_0^\infty([-1, 1])$, $\int \psi(s)ds = 1$. Then $\omega_\sigma(t)$ satisfies conditions of the theorem with $\Gamma \times]0, 2T[$ replaced by $\Gamma \times]\sigma, 2T - \sigma[$. As

$$\mathcal{M}^j \omega_\sigma = (-\partial_t)^j \omega_\sigma \in C^\infty([\sigma, 2T - \sigma[, \mathbf{L}^2(M)), \quad \text{for any } j > 0,$$

we have in particular that $\omega_\sigma(t) \in C^2([\sigma, 2T - \sigma[, \mathbf{L}^2) \cap C^1([\sigma, 2T - \sigma[, \mathbf{H})$. By the above, $\partial_t \omega_\sigma(t) = 0$ in $K_\sigma(\Gamma, T)$, where

$$K_\sigma(\Gamma, T) = \{(x, t) \mid \tilde{\tau}(x, \widetilde{M} \setminus M) < T - \sigma - |T - t|\}.$$

As $\partial_t \omega_\sigma(t) \rightarrow \partial_t \omega(t)$ in the distribution sense, the result follows. $\square$

Remark 1.13. The article [16], based on results of Tataru [62, 63] deals with scalar ϵ and μ . However, due to the single velocity of the wave propagation, it is, in principle, possible to generalize it to the scalar impedance case. Another way to prove the desired unique continuation for sufficiently smooth solutions of the equation (23) is to use the simplified version of Tataru's construction, given in [25, sec. 2.5]. There, the unique continuation result is based on local Carleman estimates for the solutions of the scalar wave equation, $u_{tt} - a_{ij}(x)\partial_i\partial_j u + A_1(x, D)u = 0$, where $A_1(x, D)$ is the first-order differential operator. These estimates utilized a function $\phi(x, t)$ that is pseudoconvex with respect to the metric a_{ij} , and absorbed the perturbation due to $A_1(x, D)$ into the main terms of the Carleman estimates. By (22) and (23), the operator $\mathcal{M}^2$ is in local coordinates a principally diagonal operator with the same second order differential operator, $g^{ij}\partial_i\partial_j$, acting on all components of $\omega(t)$. As in [25], one can treat the first-order terms as a perturbation and obtain the desired Carleman estimate. In this manner, the constructions in [25] can be word-by-word generalized to the considered case of Maxwell's equations with scalar wave impedance.

Remark 1.14. It is clear from the above arguments that if $\omega(t)$ is a weak solution of the initial boundary value problem (27) and $\omega(t) \in C^\infty([0, 2T[, \mathbf{L}^2(M))$, then

$$\omega(t) \in C^\infty([0, 2T[, \mathcal{D}^\infty(\mathcal{M}_e)), \quad \omega(t) \in C^\infty(M^{\text{int}} \times]0, 2T[),$$

where we used the notation $\mathcal{D}^\infty(\mathcal{M}_e) = \bigcap_{N>0} \mathcal{D}(\mathcal{M}_e^N)$.

1.5. Controllability results. In this section we derive controllability results for Maxwell's equations. We divide these results in *local results*, i.e., controllability at short times and *global results*, where the time of control is long enough so that the controlled electromagnetic waves fill the whole manifold. Both types of results are based on the unique continuation of Theorem 1.12.

Let $\omega^f(t)$, $f \in C_0^\infty(\mathbb{R}_+, \Omega^1 \partial M)$ be a solution of Maxwell's equations in the sense of Definition 1.7 with the initial condition $\omega^f(0) = 0$. Let $\tilde{\omega}$ be the weak solution of

(27) given by (28) with $\rho = 0$ and $\tilde{\omega}(T) = \omega_0 = (0, \omega_0^1, \omega_0^2, 0)$. Similar considerations to those in the proof of Theorem 1.9, show that

$$(39) \quad (\omega^f(T), \omega_0)_{\mathbf{L}^2} = - \int_0^T \langle \mathbf{t}\omega^f(t), \mathbf{n}\tilde{\omega}(t) \rangle dt,$$

which we will refer to as the *control identity*.

1.5.1. Local controllability. In this section, we study differential 1-forms in M generated by boundary sources active for short periods of time. Instead of a complete characterization of these forms, we show that they form a sufficiently large subspace in $L^2(\Omega^1 M)$. The difficulty that prevents a complete characterization of this subspace lies in topology of the domains of influence, which can be very complicated.

Let $\Gamma \subset \partial M$ be open and $T > 0$. The *domain of influence*, $M(\Gamma, T)$, is defined as

$$(40) \quad \begin{aligned} M(\Gamma, T) &= \{x \in M \mid \tau(x, \Gamma) < T\}, \\ M(\Gamma, T) \times \{T\} &= K(\Gamma, T) \cap \{t = T\}. \end{aligned}$$

Let $C_0^\infty(]0, T[, \Omega^1 \Gamma) \subset C_0^\infty(]0, T[, \Omega^1 \partial M)$ consists of forms supported in $\overline{\Gamma} \times [0, T]$ and

$$(41) \quad X(\Gamma, T) = \text{cl}_{L^2} \{(\omega^f)^1(T) \mid f \in C_0^\infty(]0, T[, \Omega^1 \Gamma)\}.$$

Furthermore, let

$$H(\delta, M(\Gamma, T)) = \{\omega^2 \in H(\delta, \Omega^2 M) \mid \text{supp}(\omega^2) \in \overline{M(\Gamma, T)}\}.$$

For $S \subset M$, we define $H_0^1(\Omega^k S) \subset H_0^1(\Omega^k M)$ consisting of k -forms with support in $\overline{S}$.

Theorem 1.15. *For any open $\Gamma \subset \partial M$ and $T > 0$,*

$$(42) \quad \delta H_0^1(\Omega^2 M(\Gamma, T)) \subset X(\Gamma, T) \subset \text{cl}_{L^2}(\delta H(\delta, M(\Gamma, T))).$$

Proof: The right inclusion being an immediate corollary of (14), we concentrate on the left one.

Let $\omega_0^1 \in L^2(\Omega^1 M)$ satisfy

$$(43) \quad (\omega_0^1, (\omega^f)^1(T))_{L^2} = 0, \quad \text{for all } f \in C_0^\infty(]0, T[, \Omega^1 \Gamma).$$

By the Hodge decomposition (see [57]) in $L^2(\Omega^1 M)$, we have

$$(44) \quad \omega_0^1 = \widehat{\omega}_0^1 + \delta \eta_0^2,$$

where $d\widehat{\omega}_0^1 = 0$, $\mathbf{t}\widehat{\omega}_0^1 = 0$ and $\eta_0^2 \in H(\delta, \Omega^2 M)$. Thus, (43) is equivalent to

$$(45) \quad (\delta \eta_0^2, (\omega^f)^1(T))_{L^2} = 0.$$

Let $\tilde{\omega}(t)$ be a weak solution to (27) with $\rho = 0$ and the initial data at $t = T$ given by $\tilde{\omega}(T) = (0, \delta \eta_0^2, 0, 0)$. By the control identity (39), the orthogonality (43) and

the particular form of the boundary data for solutions of Maxwell's equations (31), (32), we see that

$$0 = \int_0^T \langle \mathbf{t}\omega^f(t), \mathbf{n}\tilde{\omega}(t) \rangle = \int_0^T \langle \mathbf{t}(\omega^f)^1(t), \mathbf{n}\tilde{\omega}^2(t) \rangle = \int_0^T \langle f, \mathbf{n}\tilde{\omega}^2(t) \rangle,$$

i.e., $\mathbf{n}\tilde{\omega}^2 = 0$ on $\Gamma \times]0, T[$. Since

$$\tilde{\omega}(T+t) = (0, \tilde{\omega}^1(T-t), -\tilde{\omega}^2(T-t), 0),$$

also $\mathbf{n}\tilde{\omega}^2 = 0$ on $\Gamma \times]T, 2T[$. Since $\delta\tilde{\omega}^2(t) = 0$, we see by using Proposition 1.1 that $\mathbf{n}\tilde{\omega}^2 \in C^0(\mathbb{R}, H^{-1/2}(\Omega^1\partial M))$. Hence

$$\mathbf{n}\tilde{\omega}^2 = 0 \quad \text{on } \Gamma \times]0, 2T[.$$

Therefore, by Theorem 1.12, $\partial_t\tilde{\omega}^2 = 0$ in $K(\Gamma, T)$. In particular, $d\delta\eta_0^2 = -\partial_t\tilde{\omega}^2(T) = 0$ in $M(\Gamma, T)$. In other words, if $\omega_0^1 \in X(\Gamma, T)^\perp$, then the term η_0^2 in the decomposition (44) satisfies $d\delta\eta_0^2 = 0$ in $M(\Gamma, T)$. For any $\nu^2 \in H_0^1(\Omega^2 M(\Gamma, T))$, we have therefore

$$(\delta\nu^2, \omega_0^1)_{L^2} = (\nu^2, d\delta\eta_0^2)_{L^2} = 0,$$

and thus $\delta\nu^2 \in (X(\Gamma, T)^\perp)^\perp$. This is equivalent to the left inclusion in (42). $\square$

Remark 1.16. Later in this work, we deal mainly with the time derivatives of the electromagnetic fields. Since $\omega_t^f(t) = \omega^{\partial_t f}(t)$, we see by using

$$(46) \quad X(\Gamma, T) \subset \text{cl}_{L^2} \{(\omega_t^f(T))^1 \mid f \in \dot{C}^\infty([0, T], \Omega^1\partial M)\}$$

and (14), that the inclusions (42) remain valid when $X(\Gamma, T)$ is replaced with the right hand side of (46).

1.5.2. Global controllability. This section is devoted to the study of controllability results when the control times are large enough so that the waves fill the whole manifold.

For $\Gamma \subset \partial M$ and $T > 0$, we define

$$(47) \quad Y(\Gamma, T) = \{\omega_t^f(T) \mid f \in C_0^\infty(]0, T[, \Omega^1\Gamma)\},$$

where $\Omega^1\Gamma$ is the set of 1-forms in $\Omega^1\partial M$ supported on Γ and abbreviate $Y(\partial M, T) = Y(T)$. Our objective is to characterize $Y(\Gamma, T)$ for T large enough. In the following theorem, we use the notation

$$(48) \quad \text{rad}_\Gamma(M) = \max_{x \in M} \tau(x, \Gamma), \quad \text{rad}(M) = \text{rad}_{\partial M}(M).$$

Theorem 1.17. *For open non-empty $\Gamma \subset \partial M$ and $T \geq T_0 > 2\text{rad}_\Gamma(M)$, we have $\text{cl}_{L^2(M)} Y(\Gamma, T) = Y$, where*

$$(49) \quad Y = \{0\} \times \delta H(\delta) \times d\overset{\circ}{H}(d) \times \{0\}.$$

Proof: Let $\omega(t) = \omega^f(t)$ be a solution, in the sense of Definition 1.7, of the initial boundary-value problem with $f \in C_0^\infty([0, T_0], \Omega^1\Gamma)$. Since $f = 0$ for $T \geq T_0$, we have $\mathbf{t}\omega^1(T) = 0$, and consequently,

$$\omega_t(T) = -\mathcal{M}\omega(T) = (0, \delta\omega^2(T), -d\omega^1(T), 0) \in \{0\} \times \delta H(\delta) \times d\mathring{H}(d) \times \{0\}.$$

To prove the converse, we will show that $Y(\Gamma, T)$ is dense in $\{0\} \times \delta H(\delta) \times d\mathring{H}(d) \times \{0\}$. To this end, let $\omega_0 \in \{0\} \times \delta H(\delta) \times d\mathring{H}(d) \times \{0\}$ and $\omega_0 \perp Y(\Gamma, T)$, i.e.,

$$(50) \quad (\omega_0, \omega_t(T))_{\mathbf{L}^2} = (\omega_0^1, \omega_t^1(T))_{L^2} + (\omega_0^2, \omega_t^2(T))_{L^2} = 0,$$

for any $f \in C_0^\infty([0, T_0], \Omega^1\Gamma)$.

Let $\tilde{\omega}$ be the weak solution of the problem

$$\tilde{\omega}_t + \mathcal{M}\tilde{\omega} = 0, \quad \mathbf{t}\tilde{\omega} = 0, \quad \tilde{\omega}(T) = \omega_0.$$

Observe that ω_0 satisfies $\delta\omega_0^1 = 0$ and $d\omega_0^2 = 0$, so that $\tilde{\omega}$ satisfies Maxwell's equations. Consider the function $F : \mathbb{R} \rightarrow \mathbb{R}$, $F(t) = (\tilde{\omega}(t), \omega_t(t))_{\mathbf{L}^2}$. By Maxwell's equations,

$$\begin{aligned} F_t(t) &= (\tilde{\omega}(t), \omega_{tt}(t))_{\mathbf{L}^2} + (\tilde{\omega}_t(t), \omega_t(t))_{\mathbf{L}^2} \\ &= -(\tilde{\omega}^1, \delta d\omega^1)_{L^2} - (\tilde{\omega}^2, d\delta\omega^2)_{L^2} + (d\tilde{\omega}^1, d\omega^1)_{L^2} + (\delta\tilde{\omega}^2, \delta\omega^2)_{L^2}, \end{aligned}$$

and further, by Stokes' formula (24),

$$F_t(t) = -\langle \mathbf{t}\tilde{\omega}^1(t), \mathbf{n}d\omega^1(t) \rangle - \langle \mathbf{n}\tilde{\omega}^2(t), \mathbf{t}\delta\omega^2(t) \rangle.$$

However, $\mathbf{t}\tilde{\omega} = 0$ and $\delta\omega^2 = \omega_t^1$. Thus,

$$F_t(t) = -\langle \mathbf{n}\tilde{\omega}^2(t), \mathbf{t}\omega_t^1(t) \rangle = -\langle \mathbf{n}\tilde{\omega}^2(t), f_t(t) \rangle.$$

On the other hand, since $\omega(0) = 0$, the orthogonality condition (50) implies that $F(0) = F(T) = 0$, i.e.,

$$\int_0^T \langle \mathbf{n}\tilde{\omega}^2(t), f_t(t) \rangle dt = - \int_0^T F_t(t) dt = 0.$$

Since $f \in C_0^\infty(]0, T[, \Omega^1\Gamma)$ is arbitrary, this implies that $\mathbf{n}\tilde{\omega}_t^2 = 0$ in $\Gamma \times]0, T[$. Thus, by Theorem 1.12, $\tilde{\omega}_{tt} = 0$ in the double cone $K(\Gamma, T/2)$. Since $T_0 > 2\text{rad}_\Gamma(M)$, this double cone contains a cylinder of the form $C = M \times]T/2 - s, T/2 + s[$ with some $s > 0$. (See Figure 1).

As $\tilde{\omega}_{tt}$ satisfies Maxwell's equations with a homogeneous boundary condition $\mathbf{t}\tilde{\omega}_{tt} = 0$, this implies that $\tilde{\omega}_{tt} = 0$ in $M \times \mathbb{R}$. Therefore, $\tilde{\omega}(t) = \omega_1 + t\omega_2$, where ω_1 and ω_2 do not depend on t . Again, by Maxwell's equations,

$$\omega_2 = \tilde{\omega}_t = \mathcal{M}\omega_1 + t\mathcal{M}\omega_2.$$

Therefore, $\omega_2 = \mathcal{M}\omega_1$ and $\mathcal{M}\omega_2 = 0$. But then Stokes' formula implies that

$$(\omega_2, \omega_2)_{\mathbf{L}^2} = (\omega_2, \mathcal{M}\omega_1)_{\mathbf{L}^2} = -(\mathcal{M}\omega_2, \omega_1)_{\mathbf{L}^2} = 0,$$

i.e., $\omega_2 = 0$ and $\mathcal{M}\omega_1 = 0$. Furthermore, by the choice of ω_0 ,

$$\omega_1 = \tilde{\omega}(T) = \omega_0 = (0, -\delta\nu^2, d\nu^1, 0) = \mathcal{M}\nu,$$

with $\nu \in \{0\} \times \overset{\circ}{H}(d) \times H(\delta) \times \{0\}$. By a further application of Stokes' formula,

$$(\omega_1, \omega_1)_{\mathbf{L}^2} = (\omega_1, \mathcal{M}\nu)_{\mathbf{L}^2} = -(\mathcal{M}\omega_1, \nu)_{\mathbf{L}^2} = 0,$$

i.e., $\omega_1 = 0$ and, therefore, $\omega_0 = 0$. $\square$

1.6. Generalized sources. So far, we dealt only with smooth boundary sources and the corresponding fields. Later, we need more general sources which are described in this section.

Let W^T be the wave operator,

$$W^T : C_0^\infty([0, T_0[, \Omega^1\partial M) \rightarrow Y, \quad f \mapsto \omega_t^f(T),$$

where $T \geq T_0 > 2 \operatorname{rad}(M)$. Let $\|\cdot\|_{\mathcal{F}}$ be a quasinorm on the space of boundary sources defined via W^T ,

$$(51) \quad \|f\|_{\mathcal{F}} = \|W^T f\|_{\mathbf{L}^2}.$$

By energy conservation, this norm is independent of $T \geq T_0$ and by Theorem 1.9, if the admittance map $\mathcal{Z}^T$ is given, we can evaluate $\|f\|_{\mathcal{F}}$ for $f \in C_0^\infty([0, T_0[, \Omega^1\partial M)$.

Using the standard procedure in PDE-control, e.g. [55, 40], there is a Hilbert space of *generalized boundary sources* with the norm defined by (51). Indeed, we first introduce the space $\mathcal{F}([0, T_0])$,

$$\mathcal{F}([0, T_0]) = C_0^\infty([0, T_0[, \Omega^1\partial M) / \sim,$$

where $f \sim g$ iff $W^T f = W^T g$, and then complete it with respect to the norm (51) to obtain $\overline{\mathcal{F}}([0, T_0])$. By Theorem 1.17, W^T is an isometry between $\overline{\mathcal{F}}([0, T_0])$ and Y for any $T \geq T_0 > 2 \operatorname{rad}(M)$. The elements of $\overline{\mathcal{F}}([0, T_0])$ are equivalence classes of Cauchy sequences $(f_j)_{j=1}^\infty$ and we denote them by $\hat{f} = (f_j)_{j=1}^\infty$. (This is slight abuse of notations, as $(f_j)_{j=1}^\infty$ is a representative of the equivalence class $\hat{f}$.) To put it in another way, for any $\omega_0 \in Y$, there is a sequence $(f_j)_{j=0}^\infty$ with $f_j \in C_0^\infty([0, T_0[, \Omega^1\partial M)$, defining a generalized source $\hat{f} \in \overline{\mathcal{F}}([0, T_0])$, and for the corresponding wave

$$(52) \quad \omega_t^{\hat{f}}(t) := \lim_{j \rightarrow \infty} \omega_t^{f_j}(t), \quad \text{for } t \geq T_0,$$

we have $\omega_t^{\hat{f}}(T) = \omega_0$. Since in this work T_0 is considered as a fixed parameter, we denote $\overline{\mathcal{F}}([0, T_0])$ for brevity as $\overline{\mathcal{F}}$.

We say that $\hat{h} \in \overline{\mathcal{F}}$ is a *generalized time derivative* of $\hat{f} \in \overline{\mathcal{F}}$, if for $T = T_0$,

$$(53) \quad \lim_{\sigma \rightarrow 0+} \left\| \frac{\hat{f}(\cdot + \sigma) - \hat{f}(\cdot)}{\sigma} - \hat{h} \right\|_{\overline{\mathcal{F}}} = 0,$$

and write $\widehat{h} = \mathbb{D}\widehat{f}$, or simply $\widehat{h} = \partial_t \widehat{f}$. We also need spaces with s generalized derivatives, $\mathcal{F}^s = \mathcal{D}(\mathbb{D}^s)$, with $s \in \mathbb{Z}_+$, and $\mathcal{F}^\infty = \bigcap_{s \in \mathbb{Z}_+} \mathcal{F}^s$. As in Remark 1.14, if $\widehat{f} \in \mathcal{F}^s$,

$$(54) \quad \omega_t^{\widehat{f}} \in \bigcap_{j=0}^s (C^{s-j}([T_0, \infty[, \mathcal{D}(\mathcal{M}_e^j)) \cap \text{Ran}(\mathcal{M}_e)),$$

so that $\omega_t^{\widehat{f}}(T) \in \mathbf{H}_{\text{loc}}^s(M^{\text{int}})$ for $T \geq T_0$.

We need also the dual of the space $\mathcal{D}(\mathcal{M}_e^s)$. Since $\mathbf{H}_0^s \subset \mathcal{D}(\mathcal{M}_e^s)$, we have $(\mathcal{D}(\mathcal{M}_e^s))' \subset \mathbf{H}^{-s}$. Similarly, $\mathbf{H}_0^{-s} \subset (\mathcal{D}(\mathcal{M}_e^s))'$. These facts will be used later to construct focusing sequences.

1.7. Continuation of the boundary data. Theorems 1.9 and 1.17 make possible to continue the boundary data, originally given for $t \leq T$ to larger times $t > T$, when T is large enough, by using essentially the same ideas as in the scalar case, [25, 34] (see also [10] for another continuation method).

Lemma 1.18. *Admittance map $\mathcal{Z}^T$, given for $T > 2\text{rad}(M)$, uniquely determines $\mathcal{Z}^t$ for any $t > 0$.*

Proof: Let $2\varepsilon = T - 2\text{rad}(M)$. For $f \in C_0^\infty([0, T], \Omega^1 \partial M)$, Theorem 1.17 guarantees that there is a sequence $f_n \in C_0^\infty([\varepsilon, T], \Omega^1 \partial M)$ with

$$(55) \quad \lim_{n \rightarrow \infty} \omega_t^{f_n}(T) = \omega_t^f(T) \quad \text{in } L^2(\Omega^1 M) \times L^2(\Omega^2 M),$$

or, equivalently, in terms of the energy of the field,

$$(56) \quad \lim_{n \rightarrow \infty} \mathcal{E}^T(\omega^{g_n}) = 0, \quad g_n = \partial_t(f - f_n).$$

By using Theorem 1.9 one can verify for an arbitrary sequence $(f_n)_{n=1}^\infty$ whether the convergence condition (56) is valid or not. Moreover, the condition (56) is valid for some sequence $(f_n)_{n=1}^\infty$. Thus, when map $\mathcal{Z}^T$ is given, one can find a sequence $(f_n)_{n=1}^\infty$ that satisfies condition (56).

From the definition (28) of a weak solution, (55) implies that

$$(57) \quad \lim_{n \rightarrow \infty} \mathbf{n} \partial_t(\omega^{f_n})^2|_{\partial M \times]T, \infty[} = \mathbf{n} \partial_t(\omega^f)^2|_{\partial M \times]T, \infty[}.$$

Let $h_n(x, t) = f_n(x, t + \varepsilon) \in C_0^\infty([0, T - \varepsilon])$. Since the function $\mathcal{Z}^T h_n$ determines $\mathbf{n} \partial_t(\omega^{f_n})^2|_{\partial M \times]T, T + \varepsilon[}$, we see that $\mathcal{Z}^T$ determines $\mathbf{n}(\omega^f)^2|_{\partial M \times]T, T + \varepsilon[}$. Iterating this procedure, we construct $\mathcal{Z}^t$ for any $t > 0$. $\square$

In sequel, we need $\mathcal{Z}^T$ with various values $T > 2\text{rad}(M)$. Taking into account Lemma 1.18, we denote simply by $\mathcal{Z}$ the admittance map known for all t .

Remark 1.19. The controllability results, Theorem 1.15 together with the Blachovestchenskii formula, Theorem 1.9 make it possible to verify from the knowledge of $\mathcal{Z}^T$ whether the condition $T > 2\text{rad}(M)$ holds or not. Indeed, $T \leq 2\text{rad}(M)$ if and only if for any $\varepsilon > 0$,

$$M(\partial M, (T - \varepsilon)/2) \neq M(\partial M, T/2).$$

This is equivalent to that there are $f_n \in C_0^\infty(\partial M \times]0, T/2[)$, $n = 1, 2, \dots$ such that $(\omega^{f_n})^1(T/2)$ form a Cauchy sequence in $L^2(M)$, have norm one and converge to a function that is orthogonal to all $(\omega^h)^1((T - \varepsilon)/2)$, $h \in C_0^\infty(\partial M \times]0, (T - \varepsilon)/2[)$. When $\mathcal{Z}^T$ is given, this can be verified for all f_n and h .

2. INVERSE PROBLEM

This chapter is devoted to the inverse problem of electrodynamics. Building on properties of Maxwell's equations obtained in Chapter 1, we prove the following uniqueness result.

Theorem 2.1. *The boundary ∂M and the admittance map $\mathcal{Z}^T$, $T > 2\text{rad}(M)$, uniquely determine the manifold M , the travel metric g , and the scalar wave impedance α .*

The proof of this theorem consists of several steps. The first is to reconstruct the Riemannian manifold (M, g) . Having (M, g) , we then identify boundary sources which generate electromagnetic waves focusing in a fixed point in M at time $T > 2\text{rad}(M)$. These sources are instrumental in reconstructing the impedance α . What is more, in section 2.4 we prove a generalization of main Theorem 2.1 for the case where the admittance map is given only a part of the boundary.

At the end, we return to $\mathbb{R}^3$ to characterize group of transformations of the parameters ε and μ leaving the boundary data intact.

2.1. Reconstruction of the manifold. In this section we determine the manifold M and the travel time metric g from the admittance map $\mathcal{Z}$. The idea is to use a slicing procedure to control the supports of the waves from the boundary in order to determine the set of *boundary distance functions*.

We start by fixing certain notations. Let $T_0 < T_1 < T_2$ satisfy

$$T_0 > 2\text{rad}(M), \quad T_1 \geq T_0 + \text{diam}(M), \quad T_2 \geq 2T_1.$$

Let $\Gamma_j \subset \partial M$ be arbitrary open disjoint sets and $0 < \tau_j^- < \tau_j^+ < \text{diam}(M)$ be arbitrary times, $1 \leq j \leq J$. We define a set $S = S(\{\Gamma_j, \tau_j^-, \tau_j^+\}_{j=1}^J) \subset M$ as an intersection of slices,

$$(58) \quad S = \bigcap_{j=1}^J (M(\Gamma_j, \tau_j^+) \setminus M(\Gamma_j, \tau_j^-)).$$

(See Figure 2.) Our first goal is to find, in terms of $\mathcal{Z}$, whether the set S contains an open ball or not. To this end, we use the following definition.

Definition 2.2. *The set $Q = Q(\{\Gamma_j, \tau_j^-, \tau_j^+\}_{j=1}^J) \subset \mathcal{F}^\infty$ consists of generalized sources $\hat{f}$ such that the waves, $\omega_t = \omega_t^{\hat{f}}$, satisfy*

- (i) $\omega_t^1(T_1) \in X(\Gamma_j, \tau_j^+)$, for all j , $1 \leq j \leq J$,
- (ii) $\omega_t^2(T_1) = 0$,
- (iii) $\omega_{tt}(T_1) = 0$ in $M(\Gamma_j, \tau_j^-)$, for all j , $1 \leq j \leq J$.

Observe that Maxwell's equations for $\omega_t = \omega_t^{\hat{f}}$, $\hat{f} \in Q$ imply that $\omega_{tt} = (0, \delta\omega_t^2, -d\omega_t^1, 0)$, so in particular at $t = T_1$, we have $\omega_{tt}(T_1) = (0, 0, d\eta^1, 0)$, where $\eta^1 = -\omega_t^1(T_1)$ has the support property $\text{supp}(d\eta^1) \subset S$.




FIGURE 2. The set S in the case when $J = 2$.

The central tool for reconstruction of the manifold is the following theorem.

Theorem 2.3. *Let S and Q be defined as above. Then:*

- (1) *If S contains an open ball, then $\dim(Q) = \infty$,*
- (2) *If S does not contain an open ball, then $Q = \{0\}$.*

The proof of Theorem 2.3 is given later.

Theorem 2.4. *For any $\hat{f} \in \mathcal{F}^\infty$ it is possible, given $\mathcal{Z}$, to determine whether $\hat{f} \in Q$ or not.*

Proof: Let $\hat{f} = (f_k)_{k=0}^\infty$ be a generalized source. By Remark 1.16, Condition (i) of the definition of Q is equivalent to the existence of a sequence $\hat{h} = (h_\ell)_{\ell=0}^\infty$, $h_\ell \in \dot{C}^\infty([0, \tau_j^+], \Omega^1\Gamma_j)$, such that

$$(59) \quad \lim_{k, \ell \rightarrow \infty} \|(\omega_t^{f_k})^1(T_1) - (\omega_t^{h_\ell})^1(\tau_j^+)\| = 0.$$

By the linearity of the initial boundary value problem, we have

$$\|(\omega_t^{f_k})^1(T_1) - (\omega_t^{h_\ell})^1(\tau_j^+)\| = \|(\omega^{g_{k, \ell}})^1(T_1)\|,$$

where the source $g_{k,\ell}$ is

$$g_{k,\ell}(t) = \partial_t(f_k(t) - h_\ell(t + \tau_j^+ - T_1)) \in C_0^\infty(]0, T_1[, \Omega^1 \partial M).$$

Using Lemma 1.9, we can evaluate the norm $\|(\omega^{g_{k,\ell}})^1(T_1)\|$ for various (h_ℓ) and thus verify the condition (59).

In a similar fashion, Condition (ii) is valid for $\widehat{f}$, if

$$\lim_{k \rightarrow \infty} \|(\omega_t^{f_k})^2(T_1)\| = 0,$$

which can also be verified via $\mathcal{Z}$ by Lemma 1.9.

Finally, consider Condition (iii) for $\widehat{f}$ satisfying Conditions (i) and (ii). Observe that

$$(\partial_t + \mathcal{M})\omega_{tt} = 0 \text{ in } M \times \mathbb{R}_+,$$

where $\omega_{tt} = \omega_{tt}^{\widehat{f}}$, and $\mathbf{t}\omega_{tt} = 0$ in $\partial M \times [T_0, \infty[$. If Condition (iii) holds, then, by the finite propagation speed,

$$\omega_{tt} = 0 \text{ in } K_j = \{(x, t) \in M \times \mathbb{R}_+ \mid \tau(x, \Gamma_j) + |t - T_1| < \tau_j^-\},$$

i.e., ω_{tt} vanishes in the double cone of influence of $\Gamma_j \times]T_1 - \tau_j^-, T_1 + \tau_j^-]$, for all $j = 1, \dots, J$. Therefore, in each K_j , ω_t does not depend on time, and, by Condition (ii), $\omega_t^2 = 0$ in K_j . Hence,

$$(60) \quad \mathbf{n}\omega_t^2 = \mathcal{Z}f = 0 \text{ on } \Gamma_j \times]T_1 - \tau_j^-, T_1 + \tau_j^-].$$

Conversely, if condition (60) holds together with Conditions (i) and (ii), then ω_t satisfies

$$(\partial_t + \mathcal{M})\omega_t = 0 \text{ in } M \times \mathbb{R}_+$$

with the boundary conditions

$$\mathbf{t}\omega_t^1 = 0, \quad \mathbf{n}\omega_t^2 = 0 \text{ in } \Gamma_j \times]T_1 - \tau_j^-, T_1 + \tau_j^-],$$

because $T_1 - \tau_j^- > T_0$, so that $\widehat{f} = 0$ in $\Gamma_j \times]T_1 - \tau_j^-, T_1 + \tau_j^-]$. Thus, by Theorem 1.12, $\omega_{tt} = 0$ in K_j and, in particular, Condition (iii) is valid. As (60) is given in terms of $\mathcal{Z}$, this completes the proof. $\square$

Proof of Theorem 2.3: Assume that there is an open ball $B \subset S$ and let $\varphi \in \Omega^2 M$ with $\text{supp}(\varphi) \subset\subset B$. By Theorem 1.17, there is $\widehat{f} \in \overline{\mathcal{F}}$ such that

$$(61) \quad \omega_t^{\widehat{f}}(T_1) = (0, \delta\varphi, 0, 0),$$

Clearly, $\varphi \in \mathcal{D}^\infty(\mathcal{M}_e)$, so that $\widehat{f} \in \mathcal{F}^\infty$.

Let us show that $\widehat{f} \in Q$. Conditions (i)–(ii) are immediate from (61) and Theorem 1.15. Finally, since

$$\omega_{tt}^{\widehat{f}}(T_1) = -\mathcal{M}\omega^{\widehat{f}}(T_1) = (0, 0, d\delta\varphi, 0), \quad \text{supp}(d\delta\varphi) \subset\subset B,$$

Condition (iii) is also valid. This proves the first part of the theorem.

To prove the second part, assume that S does not contain an open ball and, however, there is $\widehat{f} \in Q$, $\widehat{f} \neq 0$. Let $\omega(t) = \omega^{\widehat{f}}(t)$. Then, by Conditions (i)–(ii),

$$(62) \quad \text{supp}(\omega_t(T_1)) \subset \bigcap_{j=1}^J M(\Gamma_j, \tau_j^+) = S^+,$$

implying, due to $\omega_{tt}(T_1) = -\mathcal{M}\omega_t(T_1)$, that $\text{supp}(\omega_{tt}(T_1)) \subset S^+$. On the other hand, by Condition (iii),

$$\omega_{tt}(T_1) = 0 \quad \text{in } \bigcup_{j=1}^J M(\Gamma_j, \tau_j^-) = S^-.$$

Thus, $\text{supp}(\omega_{tt}(T_1)) \subset S^+ \setminus S^-$, which is nowhere dense in M . Since $\omega_{tt}(T_1)$ is smooth, $\omega_{tt}(T_1) = 0$, and, therefore,

$$(63) \quad d\omega_t^1(T_1) = -\omega_{tt}^2(T_1) = 0.$$

However, by Theorem 1.17,

$$\omega_t^1(T_1) = \delta\eta^2, \quad \text{with } \eta^2 \in H(\delta, \Omega^2 M).$$

Combining this equation with (63) and using $\mathbf{t}\omega_t^1(T_1) = 0$, we obtain, by Stokes' formula (24), that

$$(\omega_t^1(T_1), \omega_t^1(T_1))_{L^2} = (\delta\eta^2, \omega_t^1(T_1))_{L^2} = (\eta^2, d\omega_t^1(T_1))_{L^2} = 0,$$

i.e., $\omega_t^1(T_1) = 0$. Also, by Condition (ii), $\omega_t^2(T_1) = 0$. These imply that $\widehat{f} = 0$. □

We are now ready to construct the set of *boundary distance functions*, r_x , which are defined, for any $x \in M$, as continuous functions on ∂M ,

$$r_x : \partial M \rightarrow \mathbb{R}_+, \quad r_x(z) = \tau(x, z), \quad z \in \partial M.$$

They define the *boundary distance map* $\mathcal{R} : M \rightarrow C(\partial M)$, $\mathcal{R}(x) = r_x$, which is continuous and injective, [32, 25]. The set of all boundary distance functions, i.e., the image of $\mathcal{R}$,

$$\mathcal{R}(M) = \{r_x \in C(\partial M) \mid x \in M\},$$

can be endowed, in a natural way, with a differentiable structure and a metric tensor $\widetilde{g}$, so that $(\mathcal{R}(M), \widetilde{g})$ becomes isometric to (M, g) , see e.g. [32, 25]. Hence, in order to reconstruct M (or more precisely, the isometry type of M), it suffices to determine the set $\mathcal{R}(M)$. The following result is therefore crucial.

Theorem 2.5. *For any $h \in C(\partial M)$, it is possible, given $\mathcal{Z}$, to determine whether $h \in \mathcal{R}(M)$ or not.*

Proof: The proof is based on a discrete approximation process. First, we observe that $h \in \mathcal{R}(M)$ if and only if, for any finite subset $\{z_1, \dots, z_J\}$ of ∂M , there is an $x \in M$ with

$$h(z_j) = \tau(x, z_j), \quad 1 \leq j \leq J.$$

Denote $\tau_j = h(z_j)$. By the continuity of the distance function, $\tau : M \times \partial M \rightarrow \mathbb{R}_+$, the above condition is equivalent to the following one: For any $\varepsilon > 0$, there are open sets $\Gamma_j \subset \partial M$, $z_j \in \Gamma_j$ with $\text{diam}(\Gamma_j) < \varepsilon$, such that

$$(64) \quad \text{int} \left(\bigcap_{j=1}^J M(\Gamma_j, \tau_j + \varepsilon) \setminus M(\Gamma_j, \tau_j - \varepsilon) \right) \neq \emptyset.$$

On the other hand, by Theorem 2.3, condition (64) is equivalent to

$$\dim(Q(\{\Gamma_j, \tau_j + \varepsilon, \tau_j - \varepsilon\}_{j=1}^J)) = \infty,$$

a condition that can be verified in terms of $\mathcal{Z}$ by means of Theorem 2.4. $\square$

As a consequence, we obtain the main result of this section.

Corollary 2.6. *The knowledge of the admittance map $\mathcal{Z}$ is sufficient for the reconstruction of the manifold M and the travel time metric g .*

Having found (M, g) , we proceed to the reconstruction of the impedance α .

2.2. Focusing sequences. In this section, we construct sequences of sources, $(\hat{f}_p)_{p=1}^\infty$ with the property that $(\omega_t^{\hat{f}_p})^2(T_1) = 0$ and $\text{supp}((\omega_t^{\hat{f}_p})^1(T_1))$ converging, when $p \rightarrow \infty$, to a single point in M^{int} , i.e., the time derivative of the electric field focuses to a single point.

Let $y \in M^{\text{int}}$ and $\underline{\delta}_y$ denote the Dirac delta at y in the sense that

$$\int_M \frac{1}{\alpha} \underline{\delta}_y(x) \wedge * \phi(x) = \phi(y), \quad \text{for any } \phi \in C_0^\infty(M).$$

Since the Riemannian manifold (M, g) is already found, we can choose $\Gamma_{jp} \subset \partial M$, $0 < \tau_{jp}^- < \tau_{jp}^+ < \text{diam}(M)$, $j = 1, \dots, J(p)$, so that

$$(65) \quad S_{p+1} \subset S_p, \quad \bigcap_{p=1}^\infty S_p = \{y\}, \quad S_p = S(\{\Gamma_{jp}, \tau_{jp}^-, \tau_{jp}^+\}_{j=1}^{J(p)}).$$

Then, $Q_p = Q(\{\Gamma_{jp}, \tau_{jp}^-, \tau_{jp}^+\}_{j=1}^{J(p)})$ are spaces of boundary sources, which correspond, by Definition 2.2, to the sets S_p .

Definition 2.7. *For $y \in M^{\text{int}}$, let S_p , $p = 1, 2, \dots$, be given by (65). A sequence $(\hat{f}_p)_{p=1}^\infty$ with $\hat{f}_p \in Q_p$, is called a focusing sequence of boundary sources of order s , $s \in \mathbb{Z}_+$, if there is a distribution form A_y on M , $A_y \neq 0$, such that*

$$(66) \quad \lim_{p \rightarrow \infty} (\omega_t^{\hat{f}_p}(T_1), \eta)_{\mathbf{L}^2} = (A_y, \eta)_{\mathbf{L}^2}, \quad \text{when } \eta \in \mathcal{D}(\mathcal{M}_e^s).$$

With a slight abuse of notations, we use the same notation for the inner product in $\mathbf{L}^2$ and for the distribution duality. We denote a focusing sequences, converging to y , by $\tilde{f}_y = (\hat{f}_p)_{p=1}^\infty$.

The following theorem characterizes a class of limit distributions that can be produced by focusing sequences. This class is large enough for our further goal to solving inverse problem. What is more, the sequences from this class can be constructed via the admittance map.

Theorem 2.8. (1) Let $y \in M^{\text{int}}$ and $(\hat{f}_p)_{p=1}^\infty$ be a sequence of boundary sources, $\hat{f}_p \in Q_p$. Given the admittance map, $\mathcal{Z}$, it is possible to determine, for any $s \in \mathbb{Z}_+$, whether $(\hat{f}_p)$ is a focusing sequence of order s or not.

(2) Let $\tilde{f}_y$ be a focusing sequence. Then $\text{supp}(A_y) = \{y\}$.

(3) For $s = 3$, the limit distribution A_y has the form

$$(67) \quad A_y = (0, \delta(\lambda(y)\underline{\delta}_y), 0, 0),$$

where $\lambda(y) \in \Lambda^2 T_y^* M$.

(4) For any $y \in M^{\text{int}}$ and $\lambda(y) \in \Lambda^2 T_y^* M$, there is a focusing sequence $\tilde{f}_y$, of order $s = 3$, with $(A_y)^1 = \delta(\lambda(y)\underline{\delta}_y)$.

Proof: 1. Take $\eta \in \mathcal{D}(\mathcal{M}_e^s)$ and decompose it as $\eta = \eta_1 + \eta_2$, where

$$\eta_1 \in \mathcal{D}(\mathcal{M}_e^s) \cap Y, \quad \eta_2 \in \mathcal{D}(\mathcal{M}_e^s) \cap Y^\perp.$$

As $\mathcal{U}(t)$ in (28) is unitary in $\mathcal{D}(\mathcal{M}_e^s)$, by Theorem 1.17 there is a boundary source $\hat{h} \in \mathcal{F}^s$ such that $\eta_1 = \omega_t^{\hat{h}}(T_1)$. Observe that $(\omega_t^{\hat{f}_p}(T_1), \eta_2)_{\mathbf{L}^2} = 0$, so that $(\hat{f}_p)$ is a focusing sequence if and only if there is a limit,

$$(68) \quad (A_y, \eta)_{\mathbf{L}^2} = \lim_{p \rightarrow \infty} (\omega_t^{\hat{f}_p}(T_1), \omega_t^{\hat{h}}(T_1))_{\mathbf{L}^2}, \quad \text{when } \hat{h} \in \mathcal{F}^s.$$

By Theorem 1.9, the existence of this limit can be verified in terms of $\mathcal{Z}$.

Conversely, assume that the limit (68) does exist for all $\hat{h} \in \mathcal{F}^s$. Then, by the Principle of Uniform Boundedness, the functionals

$$\eta \mapsto (\omega_t^{\hat{f}_p}(T_1), \eta)_{\mathbf{L}^2}, \quad p \in \mathbb{Z}_+,$$

are uniformly bounded in the dual of $(\mathcal{D}(\mathcal{M}_e^s))'$. By the Banach-Alaoglu theorem, there is a weak*-convergent subsequence,

$$\omega_t^{\hat{f}_p}(T_1) \rightarrow A_y \in \left(\mathcal{D}(\mathcal{M}_e^s) \right)',$$

where A_y is the sought distribution for which (66) is valid.

2. Let $\tilde{f}_y = (\hat{f}_p)_{p=1}^\infty$ be a focusing sequence. Since $\hat{f}_p \in Q_p$, Condition (ii) of Definition 2.2 implies that $A_y = (0, A_y^1, 0, 0)$ and Conditions (i)–(iii), together with (65), yield

$$(69) \quad \text{supp}(dA_y^1) \subset \liminf_{p \rightarrow \infty} \text{supp}(d(\omega_t^{\hat{f}_p})^1(T_1)) \subset \bigcap_{p=1}^\infty S_p = \{y\}.$$

As $\omega_t^{\hat{f}_p}(T_1) \in Y$, $\delta A_y^1 = \lim_{p \rightarrow \infty} \delta(\omega_t^{\hat{f}_p})^1(T_1) = 0$. Thus,

$$(70) \quad \text{supp}(\Delta_\alpha A_y^1) \subset \{y\}.$$

On the other hand, by Condition (i) of Definition 2.2,

$$(\omega_t^{\hat{f}_p})^1(T_1) = 0 \quad \text{in} \quad M \setminus S_p^+, \quad S_p^+ = \bigcap_{j=1}^{J(p)} M(\Gamma_{jp}, \tau_{jp}^+).$$

By the definition (66) of a focusing sequence, $A_y^1 = 0$ in $M \setminus S_p^+$. As $\text{rad}(M) < \text{diam}(M)$, we can always choose Γ_{jp}, τ_{jp}^+ , so that $M \setminus S_p^+$ is non-empty. By the unique continuation principle for elliptic systems (see e.g. [20]), it then follows from the support property (70) that $\text{supp}(A_y^1) \subset \{y\}$. Since A_y is non-zero by assumption, $\text{supp}(A_y^1) = \{y\}$.

3. Let $s = 3$. By part 2. of the theorem, in local coordinates the components of A_y are finite sums of derivatives of delta-distributions. Since $A_y \in (D(\mathcal{M}_e^s))' \subset \mathbf{H}^{-3}(M)$, it follows that

$$(71) \quad A_y^1 = \sum_{i,j=1}^3 c_i^j \partial_j \underline{\delta}_y dx^i + \sum_{i=1}^3 \tilde{c}_i \underline{\delta}_y dx^i.$$

Substituting (71) into the identity $\delta A_y^1 = 0$, we obtain (67).

4. Let $\psi_p \in C_0^\infty(S_p)$, $p = 1, 2, \dots$, be 2-forms that converge to $\lambda \underline{\delta}_y$ in $H^{1-s}(\Omega^2 M)$. By the global control Theorem 1.17, there are boundary sources $\hat{f}_p$ such that $\omega_t^{\hat{f}_p}(T_1) = (0, \delta \psi_p, 0, 0)$. Then $\tilde{f}_y = (\hat{f}_p)_{p=1}^\infty$ is a desired focusing sequence. $\square$

As y runs over M^{int} , we get a parametrized family of focusing sequences $\{\tilde{f}_y\}_{y \in M^{\text{int}}}$ which defines the map $y \mapsto \lambda(y)$. However, the admittance map does not provide a direct access to the values $\lambda(y)$. Although this mapping is unknown, we have the following result.

Lemma 2.9. *Given the admittance map $\mathcal{Z}$, it is possible to determine whether the map $y \mapsto \lambda(y)$ is a 2-form valued C^∞ -function in M^{int} .*

Proof: Let $\{A_y\}_{y \in M^{\text{int}}}$ be a family of distributions of the form (67) corresponding to a family $\{\tilde{f}_y\}_{y \in M^{\text{int}}}$ of focusing sequences. Assume that $y \mapsto \lambda(y)$ is smooth, i.e.,

$\lambda \in \Omega^2 M^{\text{int}}$. Then, for any generalized source $\hat{h} = (h_j) \in \mathcal{F}^\infty$, we have

$$\begin{aligned} (A_y, \omega^{h_j}(T_1))_{\mathbf{L}^2} &= (\delta \lambda \underline{\delta}_y, (\omega^{h_j})^1(T_1))_{L^2} = (\lambda \underline{\delta}_y, d(\omega^{h_j})^1(T_1))_{L^2} \\ &= -(\lambda \underline{\delta}_y, (\omega_t^{h_j})^2(T_1))_{L^2}. \end{aligned}$$

By taking the limit $j \rightarrow \infty$ of both sides and using the notation $\langle \lambda, \eta \rangle_y = *(\lambda \wedge *\eta)$ for inner product of $\lambda, \eta \in \Lambda^k T_y^* M$, we arrive at the identity

$$(72) \quad (A_y, \omega^{\hat{h}}(T_1))_{\mathbf{L}^2} = -\langle \lambda(y), (\omega_t^{\hat{h}})^2(y, T_1) \rangle_y.$$

As $(A_y, \omega^{\hat{h}}(T_1))_{\mathbf{L}^2} = \lim_{j \rightarrow \infty} \lim_{p \rightarrow \infty} (\omega_t^{\hat{f}_{p,y}}(T_1), \omega^{h_j}(T_1))_{\mathbf{L}^2}$, we can evaluate (72) in terms of $\mathcal{Z}$ by Theorem 1.9.

Conversely, if $(A_y, \omega^{\hat{h}}(T_1))_{\mathbf{L}^2} \in C^\infty(M^{\text{int}})$ for any $\hat{h} \in \mathcal{F}^\infty$, then $\lambda(y) \in \Omega^2(M^{\text{int}})$. Indeed, by Theorem 1.17, for any $\varphi \in \Omega^1 M$, $\text{supp}(\varphi) \subset\subset M^{\text{int}}$, there is a generalized boundary source $\hat{h} \in \mathcal{F}^\infty$ with $\omega_t^{\hat{h}}(T_1) = (0, 0, -d\varphi, 0)$, and, by (72),

$$(73) \quad (A_y, \omega^{\hat{h}}(T_1))_{\mathbf{L}^2} = \langle \lambda(y), d\varphi(y) \rangle_y \in C^\infty(M^{\text{int}}).$$

As φ is arbitrary, condition (73) is equivalent to that $\lambda(y)$ is C^∞ -smooth in M^{int} . $\square$

Returning to (72), we conclude that a focusing sequence $\{\tilde{f}_y\}$ gives rise to a functional of $(\omega_t^{h_j})^2(T_1)$. It depends only on the value of $(\omega_t^{h_j})^2(T_1)$ at the point y and will be called *point evaluation functional* in the sequel. By the above result this functional is determined upto an unknown factor $\lambda(y)$. Hence, by using three proper focusing sequences, we can evaluate the 2-form $(\omega_t^{\hat{h}})^2$ at any point in M^{int} , up to a linear transformation. The possibility to control the precise form of this transformation is discussed in the next section.

Lemma 2.10. *Let $t > T_1$ and $\hat{h} \in \overline{\mathcal{F}}$. Given the admittance map $\mathcal{Z}$, it is possible to find the 2-forms*

$$(74) \quad K(y)(\omega_t^{\hat{h}}(y, t))^2, \quad y \in M^{\text{int}}.$$

Here $K(y) : \Lambda^2 T_y^* M \rightarrow \Lambda^2 T_y^* M$ is a smooth section of $\text{End}(\Lambda^2 T^* M^{\text{int}})$ having maximal rank.

Proof: Let U be a relatively open coordinate patch in M with 2-forms $\xi_k \in \Omega^2 U$, $k = 1, 2, 3$, linearly independent at any $y \in U$. If $\{\tilde{f}_k(y)\}_{y \in U}$, $k = 1, 2, 3$ are three families of focusing sequences with the corresponding limiting 2-forms $\lambda_k(y)$, we define the endomorphism $K_U(y)$ by

$$(75) \quad K_U(y)\omega^2(y) = \sum_{k=1}^3 \langle \lambda_k(y), \omega^2(y) \rangle_y \xi_k(y), \quad y \in U.$$

As we can evaluate inner products (72) by using Theorem 1.9, it is possible, for any given three families of focusing sequences $\{\tilde{f}_k(y)\}_{y \in U}$, $k = 1, 2, 3$ and $\hat{h}$, to construct

$K(y)(\omega_t^{\hat{h}}(y, t))^2$ for $y \in U$, $t > T$. Further considerations are based on the result that we formulate separately for future reference.

Proposition 2.11. *Let $U \subset M^{\text{int}}$ be open and $\xi_k \in \Omega^2 U$, $k = 1, 2, 3$, linearly independent at each $y \in U$. There are focusing sequences $\{\tilde{f}_k(y)\}_{y \in U}$ such that the corresponding endomorphism (75) is $K_U(y) = I_y$, $y \in U$, the identity in $\Lambda^2 T_y^* M$.*

Proof: Let $\lambda_k(y)$, $k = 1, 2, 3$ form the dual basis of $\xi_k(y)$, $k = 1, 2, 3$,

$$\langle \lambda_k(y), \xi_\ell(y) \rangle_y = \delta_{k\ell}.$$

It is a consequence of Theorem 2.8 that there are focusing sequences $\tilde{f}_k(y)$ giving rise to the 2-forms $\lambda_k(y)$, which shows the claim. $\square$

End of the proof of Lemma 2.10: By the above proposition, there are, for given linearly independent $\xi_k(y)$, focusing sequences $\tilde{f}_k(y)$ so that $K_U(y)$ is of maximal rank. Moreover, since $K_U \omega^2(y)$ can be evaluated for any $\omega^2 = (\omega_t^{\hat{h}})^2(T_1)$, the maximality of the rank of $K_U(y)$ can be verified via $\mathcal{Z}$.

Let U_j , $j = 1, \dots, J$, be a finite covering of M by coordinate patches and K_j the corresponding local endomorphism of the form (75) in $U_j \cap M^{\text{int}}$. As we can compute (75) for all $\hat{h} \in \mathcal{F}^\infty$, $t > T$ and $x \in U$, it is possible to verify that $K_j(y) = K_\ell(y)$ for $y \in U_j \cap U_\ell$ for all j and ℓ . As by Proposition 2.11 there are families of focusing sequences for which this is true, we can construct the desired endomorphism. $\square$

2.3. Reconstruction of the wave impedance. So far, we have found the waves $(\omega_t^{\hat{h}})^2(t)$, $t > T_1$, up to a linear transformation K which, at this stage, is unknown. Since the choice of the focusing sequences is non-unique, we will choose them in such a manner that the endomorphism K becomes as simple as possible, i.e., $K = c_0 I$, an identity up to a constant multiplier. The first step in this direction is to consider the polarization of the *electric Green's function*, defined as the solution of the following initial boundary value problem,

$$\begin{aligned} (\partial_t + \mathcal{M})G_e(x, y, t) &= 0 \text{ in } M \times \mathbb{R}_+, \\ \mathbf{t}G_e(x, y, t) &= 0 \text{ in } (x, t) \in \partial M \times \mathbb{R}_+, \\ G_e(x, y, t)|_{t=0} &= (0, \delta(\lambda \underline{\delta}_y), 0, 0). \end{aligned} \tag{76}$$

Sometimes, we denote $G_e(x, y, t) = G_e(x, y, t; \lambda)$ to indicate the source $\lambda \in \Lambda^2 T_y^* M$. Assume that $\tilde{h} = \tilde{h}_y$ is a focusing sequence that produces a wave focusing at y , the corresponding 2-form being λ . Since the boundary sources are off when $t > T_1$, we must have

$$G_e(x, y, t) = \omega_t^{\tilde{h}}(x, t + T_1). \tag{77}$$

On the other hand, by Lemma 2.10, we can calculate the 2-forms $K(x)(\omega_t^{\tilde{h}})^2(x, t+T_1)$ for $x \in M^{\text{int}}$ and $t > 0$. Hence, we know the electric Green's function up to a linear transformation.

Let us denote by $\Phi = \Phi^\lambda(x, y, t)$ the standard Green's 2-form, satisfying

$$\begin{aligned} (\partial_t^2 + \Delta_\alpha^2)\Phi(x, y, t) &= 0 \text{ in } M \times \mathbb{R}_+, \\ (78) \quad \Phi(x, y, t)|_{\partial M \times \mathbb{R}_+} &= 0, \\ (79) \quad \Phi(x, y, 0) &= 0, \quad \Phi_t(x, y, 0) = \lambda(y)\underline{\delta}_y(x), \end{aligned}$$

where $\lambda(y) \in \Lambda^2 T_y^* M$ and the boundary condition in (79) means that all three components of Φ vanish on $\partial M \times \mathbb{R}_+$.

Let $\tilde{G}_e = \tilde{G}_e(x, y, t)$ be defined as

$$(80) \quad \tilde{G}_e = (\partial_t - \mathcal{M})(0, \delta\Phi, 0, 0) = (0, \partial_t \delta\Phi, -d\delta\Phi, 0).$$

As $(\partial_t^2 + \Delta_\alpha^2) = (\partial_t + \mathcal{M})(\partial_t - \mathcal{M})$, $\tilde{G}_e$ satisfies the complete Maxwell system and, by (79), the initial condition in (76). By the unit propagation speed, $\tilde{G}_e = 0$ near $\partial M \times]0, \tau(y, \partial M)[$, satisfying the boundary condition in (76). Thus, $\tilde{G}_e(x, y, t) = G_e(x, y, t)$ for $t < \tau(y, \partial M)$.

To further the study of G_e , we formulate the following result proved in the Appendix.

Lemma 2.12. *For every $y \in M^{\text{int}}$ there is an open neighborhood $U \subset M^{\text{int}}$ of y , a positive t_y and a mapping $Q_y(x)$ that is smooth with respect to $x \in U$, where $Q_y(x) : \Lambda^2 T_y^* M \rightarrow \Lambda^2 T_x^* M$ is bijective, such that*

$$(81) \quad \Phi(x, y, t) = Q_y(x)\lambda\underline{\delta}(t^2 - \tau^2(x, y)) + r(x, y, t), \quad (x, t) \in U \times]0, t_y[.$$

Moreover, with some smooth $Q_y^p(x) : \Lambda^2 T_y^* M \rightarrow \Lambda^2 T_x^* M$, $p = 1, 2$ and $C^{1,1}$ -smooth 2-form $\hat{r}(x, y, t)$, the remainder can be written as

$$(82) \quad r(x, y, t) = \sum_{p=1,2} Q_y^p(x)\lambda(t^2 - \tau^2(x, y))_+^{p-1} + \hat{r}(x, y, t).$$

By (80), it follows from (81) that, for sufficiently small t ,

$$(83) \quad G_e = (0, G_e^1, G_e^2, 0) + r_1,$$

where

$$G_e^1 = -2t * (d\tau^2 \wedge *Q_y\lambda)\underline{\delta}^{(2)}(t^2 - \tau^2), \quad G_e^2 = d\tau^2 \wedge *(d\tau^2 \wedge *Q_y\lambda)\underline{\delta}^{(2)}(t^2 - \tau^2),$$

and r_1 is linear combination of a bounded function, the delta distribution on $\partial B_y(t)$ and its first derivative, $B_y(t)$ being the ball of radius t centered in y . Using Lemma 2.10 and (77) together with (83), we obtain the following result.

Lemma 2.13. *Given the admittance map $\mathcal{Z}$, it is possible to find the distribution 2-form*

$$K(x)G_e^2(x, y, t) = K(x)(\tilde{\omega}_t^h)^2(x, t + T_1),$$

where $K \in \text{End}(\Omega^2 M^{\text{int}})$ and $t > 0$. Moreover, the leading singularity of this form when $0 < t < t_y$ determine the 2-form

$$(84) \quad K(x)(d\tau^2(x, y) \wedge *(d\tau^2(x, y) \wedge *Q_y(x)\lambda)), \quad x \in \partial B_y(t).$$

The linear transformation $K(x)$ of Lemma 2.10 depends on $\tilde{f}_k(x)$, $\xi_k(x)$, $k = 1, 2, 3$. Our next goal is to formulate conditions, in terms of $\mathcal{Z}$, on $\tilde{f}_k, \xi_k$ to make K isotropic, i.e.,

$$(85) \quad K(x) = c(x)I, \quad c \in C^\infty(M^{\text{int}}), \quad c(x) \neq 0.$$

To this end, observe that for $\lambda \in \Lambda^2 T_y^* M$,

$$(86) \quad \mathbf{t}_{B_y(t)}(d\tau^2 \wedge *(d\tau^2 \wedge *Q_y\lambda)) = 0,$$

where $\mathbf{t}_{B_y(t)}\omega^k$ is the tangential component of ω^k on $\partial B_y(t)$. Physically, condition (86) corresponds to the orthogonality of the polarization of the magnetic flux density and the direction of wave propagation. (See Figure 3.) If K is isotropic, we have

$$(87) \quad \mathbf{t}_{B_y(t)}\left(K(d\tau^2 \wedge *(d\tau^2 \wedge *Q_y\lambda))\right) = 0.$$




FIGURE 3. Vector $\vec{v}$ is the right polarization of the electromagnetic wave in the plane $M \times \{t\}$. The reconstructed polarization $\vec{w}$ has wrong direction, if the transformation matrix $K(x)$ is not isotropic.

Conversely, we show that condition (87) for all $y \in M^{\text{int}}$ and $t < t_y$ guarantees that K is isotropic. What is more, the condition (87) is verifiable from the knowledge of $\mathcal{Z}$. Indeed, for $\lambda(y) \in \Lambda^2 T_y^* M$ and $t = \tau(x, y)$, (87) means that $K(d\tau^2 \wedge *(d\tau^2 \wedge *Q_y\lambda))$ is normal to $T_x \partial B_y(t) \subset T_x M$, i.e., for vectors $X, Y \in T_x \partial B_y(t)$, we have

$$K(x)(d\tau^2(x, y) \wedge *(d\tau^2(x, y) \wedge *Q_y(x)\lambda(y)))(X, Y) = 0.$$

Observe that when $\lambda(y)$ runs through $\Lambda^2 T_y^* M$, then $*(Q_y(x)\lambda(y))$ runs through $T_x^* M$. Now we may vary y and t with fixed x such that $\tau(x, y) = t$, making $T_x \partial B_y(t)$ run through the Grassmannian manifold $G_{3,2}(T_x M)$. Transformation $K(x)$ is kept

invariant in this variation. Hence, we deduce that $K(x)$ keeps any 2-dimensional subspace of $\Lambda^2 T_x^* M$ invariant, so it must be isotropic as claimed.

Assume that the focusing sequences used for the point evaluation functionals are chosen so that $K(x) = c(x)I$. For any generalized source $\hat{f} \in \overline{\mathcal{F}}$, we may thus evaluate

$$(\tilde{\omega}_t^{\hat{f}})^2(x, T_1) = c(x)(\omega_t^{\hat{f}})^2(x, T_1),$$

with yet unknown $c(x)$. Since $\omega^{\hat{f}}$ satisfies Maxwell's equations, we have

$$d(\tilde{\omega}_t^{\hat{f}})^2 = dc \wedge (\omega_t^{\hat{f}})^2 + cd(\omega_t^{\hat{f}})^2 = dc \wedge (\omega_t^{\hat{f}})^2.$$

The global control Theorem 1.17 thus asserts that $c(x) = c_0$ is equivalent to

$$(88) \quad d(\tilde{\omega}_t^{\hat{f}})^2(x, T_1) = 0, \quad \text{for all } \hat{f} \in \overline{\mathcal{F}},$$

a condition that is verifiable from the knowledge of $\mathcal{Z}$. Hence, the focusing sequences used for point evaluation can be chosen such that $c(x) = c_0 \neq 0$.

To proceed with reconstruction of α , consider the inner product,

$$(89) \quad \int_M (\tilde{\omega}_t^{\hat{f}})^2(x, T_1) \wedge *(\tilde{\omega}_t^{\hat{h}})^2(x, T_1) = c_0^2 \int_M (\omega_t^{\hat{f}})^2(x, T_1) \wedge *(\omega_t^{\hat{h}})^2(x, T_1),$$

which can be found via $\mathcal{Z}$. On the other hand, by Theorem 1.9, $\mathcal{Z}$ determines the energy inner product,

$$\frac{1}{2} \int_M \frac{1}{\alpha(x)} (\omega_t^{\hat{f}})^2(x, T_1) \wedge *(\omega_t^{\hat{h}})^2(x, T_1).$$

By choosing the boundary source $\hat{h} = \hat{h}_j$ such that $\tilde{h} = (\hat{h}_j)_{j=1}^\infty$ is a focusing sequence and by comparing the above inner products at the limit $j \rightarrow \infty$, we recover the value $c_0^2 \alpha(x)$ at any point $x \in M$.

Finally, we notice e.g. by considering the energy integrals that the admittance map has the scaling property $\mathcal{Z}_{(M,g,c_0^2\alpha)} = c_0^{-2} \mathcal{Z}_{(M,g,\alpha)}$, with evident notations. Therefore, given $\mathcal{Z}$ and $(g, c_0^2\alpha)$ already reconstructed, it is also possible to determine c_0 and hence α . This completes the proof of Theorem 2.1. $\square$

2.4. Data given on the part of the boundary. In this section, we generalize the proof of Theorem 2.1 for the case when the data is given on a non-empty open subset $\Gamma \subset \partial M$. In this case, instead of the complete admittance map $\mathcal{Z}^T$ we are given the local admittance map $\mathcal{Z}_\Gamma^T$, defined by

$$\mathcal{Z}_\Gamma^T f = \mathcal{Z}^T f|_{\Gamma \times]0, T[}, \quad f \in \dot{C}^\infty([0, T], \Omega^1 \Gamma),$$

where $\Omega^1 \Gamma$ is the space of 1-forms $f \in \Omega^1 \partial M$ supported on Γ . Denote $\mathcal{Z} = \mathcal{Z}^T$ with $T = \infty$ and recall that $\text{rad}_\Gamma(M)$ is the geodesic radius of M with respect to Γ , see (48).

Theorem 2.14. *Given Γ , the local admittance map $\mathcal{Z}_\Gamma^T$, $T > 2\text{rad}_\Gamma(M)$, uniquely determines the manifold M , the metric g , and the scalar wave impedance α .*

Proof. Here we use notations of section 1.6. By Theorem 1.17 we have that the set $\mathcal{F}_\Gamma = C_0^\infty([0, T_0], \Omega^1\Gamma)/\sim$ with $T > T_0 > 2\text{rad}_\Gamma(M)$ is a dense subset of $\overline{\mathcal{F}}$. Thus we can identify $\overline{\mathcal{F}}_\Gamma$ with $\overline{\mathcal{F}}$. This makes it possible to use, when the data is given on a part of the boundary, all the results about generalized sources obtained in section 1.6 for the whole boundary. In particular, we can define sets $\mathcal{F}_\Gamma^s \subset \overline{\mathcal{F}}_\Gamma$ that can be identified with $\mathcal{F}^s$.

Exactly as in section 1.4 we can show that the local admittance map $\mathcal{Z}_\Gamma^T$, $T > 2\text{rad}_\Gamma(M)$, determine the map $\mathcal{Z}_\Gamma^t$ for all $t > 0$, i.e., the map $\mathcal{Z}_\Gamma$.

Our first aim is to reconstruct (M, g) near Γ . For this, let $\theta_\Gamma : \Gamma \rightarrow \mathbb{R}$ be

$$\theta_\Gamma(z) = \sup\{s > 0 : \tau(\gamma_{z,\nu}(s), \Gamma) = s\}$$

and

$$M_\Gamma = \{\gamma_{z,\nu}(s) \in M : z \in \Gamma, 0 \leq s < \theta_\Gamma(z)\},$$

where $\gamma_{z,\nu}(s)$ is the geodesic starting from $z \in \partial M$ in the normal direction.

Lemma 2.15. *Given Γ , the local admittance map $\mathcal{Z}_\Gamma$ determines the function $\theta_\Gamma : \Gamma \rightarrow \mathbb{R}$, the Riemannian manifold (M_Γ, g) , and the wave impedance α on M_Γ .*

Proof: Let $z \in \Gamma$. Using notations of section 2.1 we see that $s \leq \theta_\Gamma(z)$ if and only if $S = M(\Gamma_z, s) \setminus M(\Gamma, s - \varepsilon)$ has non-empty interior for all open $\Gamma_z \subset \Gamma$ containing z and $\varepsilon > 0$. In turn, $S = (M(\Gamma_z, s) \setminus M(\Gamma_z, 0)) \cap (M(\Gamma, s) \setminus M(\Gamma, s - \varepsilon))$ is of the form (58). Thus, using Theorem 2.4 with $\mathcal{Z}_\Gamma$ instead of $\mathcal{Z}$, we can find out whether S has non-empty interior or not. Thus we can find $\theta_\Gamma(z)$.

At this stage, we can proceed in a similar manner to the proof of Theorem 2.5 to find functions $R_\Gamma(M_\Gamma) = \{r_x|_\Gamma : x \in M_\Gamma\}$. To do this, we just use the procedure presented in the proof of Theorem 2.5 but consider only functions $h \in C(\Gamma)$ that have a unique global minimum, say $z_0 \in \Gamma$, with $h(z_0) < \theta_\Gamma(z_0)$. After construction of this set, we see as in [25, Sect. 4.4] that the set $R_\Gamma(M_\Gamma)$ determines the Riemannian manifold (M_Γ, g) .

Reconstruction of α in M_Γ follows the same route as with data given on the whole boundary by restricting our attention to focusing sequences corresponding to points $y \in M_\Gamma$ and using identification of $\mathcal{F}_\Gamma^s$ with $\mathcal{F}^s$. $\square$

In the next step we will show that we can find the admittance map on the boundary of an arbitrary ball $B \subset M_\Gamma$. We will denote by $\mathcal{Z}_{\partial B}$ the local admittance map defined by using the manifold $M \setminus B$ instead of M and ∂B instead of Γ . For similar arguments in the scalar case, see [26].

Proposition 2.16. *Given (M_Γ, g, α) and the map $\mathcal{Z}_\Gamma$ for (M, g, α) , we can find the local admittance map $\mathcal{Z}_{\partial B}$ for $(M \setminus B, g, \alpha)$.*

Proof. First we observe that (M_Γ, g, α) and $\mathcal{Z}_\Gamma$ determine the values of the electric Green's function $G_e^2(x, y, t; \lambda)$ for any $x, y \in M_\Gamma$, $t > 0$, and $\lambda \in \Lambda^2 T_y^* M$. This result is proven in section 2.3 in the case when the admittance map is given on the whole boundary and the proof can be directly extended to the considered case.

Consider now the initial boundary value problem

$$(90) \quad \partial_t \eta + \mathcal{M}\eta = \kappa, \quad \text{in } M \times \mathbb{R}_+, \quad \mathbf{t}\eta|_{\partial M \times \mathbb{R}_+} = 0, \quad \eta(0) = 0,$$

where $\kappa = (0, \delta\beta, 0, 0)$ with $\beta \in \dot{C}^\infty(\mathbb{R}_+, \Omega^2 B)$ and denote its solution by $\eta = \eta_\beta = (0, \eta^1, \eta^2, 0)$. Writing η^2 in terms of the electric Green's function we obtain

$$(91) \quad \eta^2(x, t) = \int_{\mathbb{R}_+} \int_B G_e^2(x, y, t - t'; \frac{\beta(y, t')}{\alpha(y)}) dV_g(y) dt',$$

where dV_g is the Riemannian volume measure on (M, g) . Using equation (90) we also find

$$(92) \quad \eta^1(x, t) = \int_0^t (\delta\eta^2(x, t') + \delta\beta(x, t')) dt'.$$

We continue the proof with the following lemma;

Lemma 2.17. *Let $\omega = (0, \omega^1, \omega^2, 0) \in \dot{C}^\infty(\mathbb{R}_+, \Omega M)$ be a solution of Maxwell's equations (17) and (18) in $(M \setminus B) \times \mathbb{R}_+$ which satisfies the electric boundary condition $\mathbf{t}\omega = 0$ on $\partial M \times \mathbb{R}_+$ and initial condition $\omega(0) = 0$. Then there is $\beta \in \dot{C}^\infty(\mathbb{R}_+, \Omega^2 B)$ such that the solution η_β of initial boundary value problem (90) coincides with ω_{tt} in $(M \setminus B) \times \mathbb{R}_+$.*

Proof. Let $\tilde{\omega} = (0, \tilde{\omega}^1, \tilde{\omega}^2, 0) \in \dot{C}^\infty(\mathbb{R}_+, \Omega M)$ be an arbitrary smooth continuation of ω into $B \times \mathbb{R}_+$. Let

$$\rho = (0, \rho^1, \rho^2, 0), \quad \rho^1 = -\delta d\tilde{\omega}^1, \quad \rho^2 = -d\delta\tilde{\omega}^2.$$

Then $\rho = \omega_{tt}$ in $(M \setminus B) \times \mathbb{R}_+$, and ρ satisfies Maxwell's equations

$$\begin{aligned} \rho_t^1 - \delta\rho^2 &= \delta da^1, & a^1 &= -\tilde{\omega}_t^1 + \delta\tilde{\omega}^2, \\ \rho_t^2 + d\rho^1 &= d\delta a^2, & a^2 &= -\tilde{\omega}_t^2 - d\tilde{\omega}^1, \end{aligned}$$

in $M \times \mathbb{R}_+$. Then $\eta = (0, \rho^1 - \delta a^2, \rho^2, 0)$ satisfies the initial boundary value problem (90) with $\beta = da^1 - a_t^2$ supported in $B \times \mathbb{R}_+$. In particular, $\omega_{tt} = \eta_\beta$ in $(M \setminus B) \times \mathbb{R}_+$. $\square$

To complete the proof of Proposition 2.16 we start with an arbitrary $\beta \in \dot{C}^\infty(\mathbb{R}_+, \Omega^2 B)$ and find, using formulae (91), (92), the wave $\eta_\beta(x, t)$ for $x \in M_\Gamma$. Let $\omega(x, t)$ be now

defined as

$$(93) \quad \begin{aligned} \omega^0(x, t) &= 0, \quad \omega^1(x, t) = \int_0^t \int_0^{t'} \eta_\beta^1(x, t'') dt'' dt', \\ \omega^2(x, t) &= \int_0^t \int_0^{t'} \eta_\beta^2(x, t'') dt'' dt', \quad \omega^3(x, t) = 0. \end{aligned}$$

Then $\omega(t)$ is a solution of the initial-boundary value problem,

$$\begin{aligned} \omega_t + \mathcal{M}\omega &= 0 \quad \text{in } (M \setminus B) \times \mathbb{R}_+, \quad \omega(0) = 0, \\ \mathbf{t}\omega|_{\partial M \times \mathbb{R}_+} &= 0, \quad \mathbf{t}\omega|_{\partial B \times \mathbb{R}_+} = (0, f_\beta, -\int_0^t df_\beta), \end{aligned}$$

where

$$(94) \quad f_\beta = \int_0^t \int_0^{t'} \mathbf{t}\eta_\beta^1(x, t'') dt'' dt' \in \dot{C}^\infty(\mathbb{R}_+, \Omega^1 \partial B).$$

Using again formulae (91), (92), we see that (M_Γ, g, α) , $\mathcal{Z}_\Gamma$ determine the map

$$(95) \quad f_\beta^1 \longrightarrow \mathbf{n}\omega^2|_{\partial B \times \mathbb{R}_+} = \int_0^t \int_0^{t'} \mathbf{n}\eta_\beta^2(x, t'') dt'' dt' \in \dot{C}^\infty(\mathbb{R}_+, \Omega^1 \partial B)$$

for any f_β^1 of form (94). As according to Lemma 2.17. the map $\beta \rightarrow f_\beta^1$ is a surjective map from $\dot{C}^\infty(\mathbb{R}_+, \Omega^2 B)$ onto $\dot{C}^\infty(\mathbb{R}_+, \Omega^1 \partial B)$, the map (95) determines $\mathcal{Z}_\Gamma$. This proves Proposition 2.16. $\square$

Having found $\mathcal{Z}_{\partial B}$ we construct the Riemannian manifold $M_{\partial B} \subset M \setminus B$, metric g on $M_{\partial B}$ and impedance α on $M_{\partial B}$. Here $M_{\partial B}$ is defined in a similar way as M_Γ changing M to $M \setminus B$ and Γ to ∂B . Combining this with the previous results, we find the part $M_\Gamma \cup M_{\partial B}$ of M as well as the metric g and the wave impedance α on it. Iterating this procedure, we reconstruct, in finite number of steps, the whole manifold (M, g, α) . For detail, see [25, Sect 4.4.9]. This proves Theorem 2.14. $\square$

2.5. Inverse problem for Maxwell equations in $\mathbb{R}^3$. In this section, the uniqueness results for Maxwell's equations on a manifold are used to characterize the non-uniqueness of inverse problems for Maxwell's equations (1)–(2) in a bounded domain of $M \subset \mathbb{R}^3$ with the Euclidean metric $(g_0)_{ij} = \delta_{ij}$.

Let $M_j \subset \mathbb{R}^3$, $j = 1, 2$, be two bounded smooth closed domains with a common part Γ of their boundaries, $\Gamma \subset \partial M_1 \cap \partial M_2$. Let ϵ_j and μ_j , $j = 1, 2$ be permittivity and permeability matrices in M_j , respectively, with $\mu_j = \alpha_j^2 \epsilon_j$, with $\alpha_j > 0$ being the corresponding scalar impedances. Assume that the local admittance maps $\mathcal{Z}_{\Gamma, j}$ for (M_j, ϵ_j, μ_j) coincide. By Theorem 2.14, both (M_1, ϵ_1, μ_1) and (M_2, ϵ_2, μ_2) correspond to the same abstract manifold $(\widetilde{M}, \widetilde{g}, \widetilde{\alpha})$ which is uniquely determined by $\mathcal{Z}_{\Gamma, j}$ with the part Γ corresponding to a part $\widetilde{\Gamma} \subset \partial \widetilde{M}$. This implies that there are embeddings $F_j : \widetilde{M} \rightarrow M_j \subset \mathbb{R}^3$ of the manifold $\widetilde{M}$ in the Euclidean space such that the

metric tensors and the wave impedances satisfy $\tilde{g} = (F_j)^* g_j$ and $\tilde{\alpha} = (F_j)^* \alpha_j$ and $F_1|_{\tilde{\Gamma}} = F_2|_{\tilde{\Gamma}}$. Recall that g_j are determined by expression (10) with ε_j and μ_j in place of ε, μ . Embeddings F_j induce a diffeomorphism

$$(96) \quad \Phi = F_2 \circ F_1^{-1} : M_1 \rightarrow M_2, \quad \Phi|_{\Gamma} = \text{id}.$$

Consider two vector fields X_1 and Y_1 in M_1 , and denote $X_2 = D\Phi X_1$, $Y_2 = D\Phi Y_1$. The electric energy inner product for the corresponding 1-forms $\omega^1, \eta^1 \in \Omega^1 M$ is invariant, i.e., we have

$$\int_{M_1} g_0(X_1, \epsilon_1 Y_1) dV_0 = \int_{\tilde{M}} \frac{1}{\tilde{\alpha}} \omega^1 \wedge * \eta^1 = \int_{M_2} g_0(X_2, \epsilon_2 Y_2) dV_0.$$

On the other hand, as $X_2 = D\Phi X_1$ and $Y_2 = D\Phi Y_1$,

$$\int_{M_2} g_0(X_2, \epsilon_2 Y_2) dV_0 = \int_{M_1} g_0(X_1, \Phi^* \epsilon_2 Y_1) dV_0,$$

where

$$(97) \quad \Phi^* \epsilon_2 = \frac{1}{\det D\Phi} (D\Phi)^T (\epsilon_2 \circ \Phi) D\Phi.$$

Since X_1 and Y_1 are arbitrary, we must have $\epsilon_1 = \Phi^* \epsilon_2$. Similar reasoning shows that $\mu_1 = \Phi^* \mu_2$.

Thus we have proven the following result.

Theorem 2.18. *Let $M_1, M_2 \subset \mathbb{R}^3$ be bounded smooth domains and $\Gamma \subset \partial M_1 \cap \partial M_2$ be open and non-empty. Let $\mathcal{Z}_{\Gamma,1}$ and $\mathcal{Z}_{\Gamma,2}$ be the local admittance maps corresponding to (M_1, ϵ_1, μ_1) and (M_2, ϵ_2, μ_2) , respectively. Then $\mathcal{Z}_{\Gamma,1} = \mathcal{Z}_{\Gamma,2}$ if and only if there is a diffeomorphism $\Phi : M_1 \rightarrow M_2$, $\Phi|_{\Gamma} = \text{id}$ and $\epsilon_1 = \Phi^* \epsilon_2$, $\mu_1 = \Phi^* \mu_2$.*

Remark 2.19. It follows from (97) that ϵ and μ do not transform like tensors of type (1,1). This is due to the special role played by the underlying Euclidean metric $g_0^{ij} = \delta^{ij}$, which is not changed by diffeomorphisms Φ . These transformations were observed also in the study of the Calderón inverse conductivity problem. It is shown in [59] that, for $\Omega \subset \mathbb{R}^2$, boundary measurements determine the anisotropic conductivity up to same group of transformations as described in Theorem 2.18. For $n \geq 3$, a similar result is conjectured, based on the analysis of the linearized inverse problem, see [60]. The Calderón problem is closely related to the inverse problem for Maxwell's equations, as the low-frequency limit of $\mathcal{Z}$ is related to the Dirichlet-to-Neumann map for the conductivity equation [42].

When ϵ and μ are isotropic, we obtain the following uniqueness result.

Theorem 2.20. *Let $M \subset \mathbb{R}^3$ be a bounded smooth domain, $\Gamma \subset \partial M$ be open and non-empty, ϵ and μ be smooth positive functions on $\overline{M}$ and $\mathcal{Z}_{\Gamma}$ be a local admittance map for (M, ϵ, μ) . Then Γ and $\mathcal{Z}_{\Gamma}$ determine (M, ϵ, μ) uniquely.*

Note that the knowledge of M is not a priori assumed in the above theorem.

Proof. Assume that for (M_1, ϵ_1, μ_1) and (M_2, ϵ_2, μ_2) such that $\Gamma \subset \partial M_1 \cap \partial M_2$ we have $\mathcal{Z}_{\Gamma,1} = \mathcal{Z}_{\Gamma,2}$. Then there is a diffeomorphism $\Phi : M_1 \rightarrow M_2$ satisfying $\Phi|_{\Gamma} = \text{id}$ and $\epsilon_1 = \Phi^* \epsilon_2$, $\mu_1 = \Phi^* \mu_2$. Since ϵ_1 and ϵ_2 are isotropic, it follows from the Liouville theorem that Φ is conformal. Since $\Phi|_{\Gamma} = \text{id}$, it follows that Φ is identity. $\square$

2.6. Outlook. There are several direction to which the present work can be extended.

1. A natural inverse problem is the inverse boundary spectral problem for the electric Maxwell operator $\mathcal{M}_e$. The problem is to determine the metric g and wave impedance α , or, in the other words, ϵ and μ from the non-zero eigenvalues λ_j of $\mathcal{M}_e$ and the normal components of the corresponding eigenforms on ∂M . This problem was studied in, e.g. [41], for the scalar Maxwell's equations. For the considered anisotropic case, this requires significant modifications of the method developed in this paper and will be published elsewhere.

2. With the uniqueness of the inverse problem in hand, the next issue is to study stability of the inverse problem and develop stable reconstruction algorithms. A general approach to these questions, in the scalar case, is introduced in [27], in terms of certain geometrical a priori bounds on (M, g) , with sharp results on conditional stability in [1]. Adding *a priori* analytical bounds on α , we intend to analyse these questions for anisotropic Maxwell's equations.

Appendix: The WKB approximation. Denote by $\Phi(x, y, t) = \Phi_{\lambda}(x, y, t)$ the Green's 2-form, i.e., the solution of

$$(98) \quad \begin{aligned} (\partial_t^2 + \Delta_{\alpha}^2) \Phi_{\lambda}(x) &= 0 \quad \text{in } M \times \mathbb{R}_+, \\ \Phi_{\lambda}(x)|_{t=0} &= 0, \quad \partial_t \Phi_{\lambda}(x)|_{t=0} = \lambda \underline{\delta}_y(x), \quad \Phi_{\lambda}(x)|_{\partial M \times \mathbb{R}_+} = 0, \end{aligned}$$

where $\lambda \in \Lambda^2 T_y^* M$. Let $B_y(\rho)$, $\rho < \tau(y, \partial M)$ be a domain of normal coordinates centered at y , so that

$$(99) \quad g^{ij}(0) = \delta^{ij}, \quad \partial_k g^{ij}(0) = 0.$$

Rewriting equations (98), componentwise, in these coordinates and using the unit propagation speed, we can, instead of (98), consider the fundamental solution, $\Phi(x, y, t)$, $t < \rho$,

$$(100) \quad \begin{aligned} \{(\partial_t^2 - g^{ij} \partial_i \partial_j) I + B^i \partial_i + C\} \Phi &= 0, \quad \text{in } M \times]0, \rho[, \\ \Phi|_{t=0} &= 0, \quad \partial_t \Phi|_{t=0} = I \underline{\delta}(x), \end{aligned}$$

where I is the 3×3 identity matrix and $B^i(x)$, $C(x)$ are smooth 3×3 matrices.

Following [15, 3], which deal with the scalar case, we search for the solution to (100) in the WKB form:

$$(101) \quad \Phi(x, t) \approx G_0(x) \underline{\delta}(t^2 - \tau^2) + \sum_{\ell \geq 1} G_\ell(x) (t^2 - \tau^2)_+^{\ell-1} / (\ell-1)!,$$

where $\tau(x, y) = |x|$. Substitution of (101) into equation (100) gives rise to the recurrent system of transport equations. The principal one is the equation for G_0 ,

$$4\tau \frac{dG_0}{d\tau}(\tau\hat{x}) + \{(g^{ij}(\tau\hat{x}) \partial_i \partial_j \tau^2 - 6) I + B^i(\tau\hat{x}) \partial_i \tau^2\} G_0(\tau\hat{x}) = 0,$$

where $\hat{x} = x/\tau$. To satisfy initial conditions in (100), we require that $G_0(0) = (2\pi)^{-1}I$. By (99), $g^{ij} \partial_i \partial_j \tau^2|_{x=0} - 6 = 0$. Also, $\partial_i \tau^2|_{x=0} = 0$. Therefore,

$$\frac{1}{4\tau} \{(g^{ij}(\tau\hat{x}) \partial_i \partial_j \tau^2 - 6) I + B^i(\tau\hat{x}) \partial_i \tau^2\}$$

is a smooth function of $(\tau, \hat{x})$, so that $G_0(x)$ is a smooth 3×3 matrix-function of $(\tau, \hat{x})$, for $\tau > 0$. Moreover, it can be shown that $G_0(x)$ is also smooth at $x = 0$.

For G_ℓ , $\ell \geq 1$, we obtain transport equations

$$\begin{aligned} 4\tau \frac{dG_\ell}{d\tau} + \{(4\ell - 6 + g^{ij}(x) \partial_i \partial_j \tau^2(x)) I + B^i(x) \partial_i \tau^2\} G_\ell \\ = [g^{ij} \partial_i \partial_j I - B^i \partial_i - C] G_{\ell-1}, \end{aligned}$$

with $G_\ell(0) = 0$. If we write $G_\ell = G_0 F_\ell$, we obtain for F_ℓ the equations

$$(102) \quad 4\tau \frac{dF_\ell}{d\tau} + 4\ell F_\ell = G_0^{-1} [g^{ij} \partial_i \partial_j I - B^i \partial_i - C] G_{\ell-1}, \quad F_\ell(0) = 0.$$

Solving the above equation, we find

$$(103) \quad F_\ell(x) = \frac{1}{4} \tau^{-\ell} \int_0^\tau G_0^{-1}(s\hat{x}) \{[g^{ij} \partial_i \partial_j I - B^i \partial_i - C] G_{\ell-1}\}(s\hat{x}) s^{\ell-1} ds,$$

which are smooth functions of x . As (100) is a hyperbolic system, the right side of (101) is the asymptotics, with respect to smoothness, of $\Phi(x, y, t)$, when $t < \rho$.

Clearly, the asymptotic expansion (101) implies decomposition (81), (82).

Acknowledgements: We would like to give our warmest thanks to professor Alexander Katchalov for numerous useful discussions. His lectures on non-stationary Gaussian beams [22, 23] at Helsinki University of Technology were paramount for our understanding of the subject. Also, we thank Helsinki University of Technology, Loughborough University and University of Helsinki for their kind hospitality and financial support. Furthermore, the financial support of the Academy of Finland, project 102175, Royal society, and EPSRC, GR/R935821/01 is acknowledged.

REFERENCES

- [1] Anderson, M., Katsuda, A., Kurylev, Y., Lassas, M., Taylor M. Geometric Convergence, and Gel'fand's Inverse Boundary Problem. *Inventiones Mathem.*, **158** (2004), 261-321.
- [2] Birman, M., Solomyak, M. The selfadjoint Maxwell operator in arbitrary domains. (Russian) *Algebra i Analiz* **1** (1989), no. 1, 96-110.
- [3] Babich V.M. The Hadamard ansatz, its analogues, generalisations and applications. *St. Petersburg Math. J.*, Vol. 3, No. **5** (1992), 937-972.
- [4] Belishev, M., Blagoveščenskii, A.S. Direct method to solve a nonstationary inverse problem for the wave equation. *Ill-Posed Problems of Math. Phys and Anal.* (Russian) 1988, 43-49.
- [5] Belishev, M. An approach to multidimensional inverse problems for the wave equation. (Russian) *Dokl. Akad. Nauk SSSR* **297** (1987), 524-527.
- [6] Belishev, M., Isakov, V., Pestov, L., Sharafutdinov, V. On the reconstruction of a metric from external electromagnetic measurements. (Russian) *Dokl. Akad. Nauk* **372** (2000), no. 3, 298-300.
- [7] Belishev, M., Kurylev, Y. To the reconstruction of a Riemannian manifold via its spectral data (BC-method). *Comm. Part. Diff. Equations* **17** (1992), 767-804.
- [8] Belishev, M., Glasman, A. A dynamic inverse problem for the Maxwell system: reconstruction of the velocity in the regular zone (the BC-method). *Algebra i Analiz* **12** (2000), 131-187; transl. *St. Petersburg Math. J.* **12** (2001), 279-316.
- [9] Belishev M., Glasman A. Boundary control of the Maxwell dynamical system: lack of controllability by topological reasons. *Mathematical and numerical aspects of wave propagation WAVES 2003*, 177-182, Springer, Berlin, 2003.
- [10] Belishev, M., Isakov, V. On the uniqueness of the reconstruction of the parameters of the Maxwell system from dynamic boundary data. (Russian) *Zap. Nauchn. Sem. POMI* **285** (2002), 15-32.
- [11] Bossavit, A. *Électromagnétisme, en vue de la modélisation*. Mathématiques & Applications 14, Springer-Verlag, 1993, xiv+174 pp.
- [12] Bossavit, A. *Computational electromagnetism. Variational formulations, complementarity, edge elements*. Academic Press Inc., San Diego, CA, 1998.
- [13] Calderón, A.-P. On an inverse boundary value problem. *Seminar on Numerical Analysis and its Applications to Continuum Physics (Rio de Janeiro, 1980)*, pp. 65-73, Soc. Brasil. Mat., Rio de Janeiro, 1980.
- [14] Colton, D., Päivärinta, L. The uniqueness of a solution to an inverse scattering problem for electromagnetic waves. *Arch. Rational Mech. Anal.* **119** (1992), 59-70.
- [15] Courant, R., Hilbert, D. *Methods of Mathematical Physics. Vol.II: Partial Differential Equations*, Interscience, 1962.
- [16] Eller, M., Isakov, V., Nakamura, G., Tataru, D. Uniqueness and stability in the Cauchy problem for Maxwell's and elasticity systems. *Nonlinear PDE and their applications. College de France Seminar*, **XIV**(2002), 329-349, 2002.
- [17] Frankel, T. *The geometry of physics*. Cambridge University Press, 1997. 654 pp.
- [18] Gel'fand, I.M. Some aspects of functional analysis and algebra. *Proc. Intern. Cong. Math.*, **1** (1954) (Amsterdam 1957), 253-277.
- [19] Greenleaf, A., Uhlmann, G. Local uniqueness for the Dirichlet-to-Neumann map via the two-plane transform. *Duke Math. J.* **108** (2001), 599-617.
- [20] Isakov, V. Carleman type estimates and their applications. In: K. Bingham, Y. Kurylev, E. Somersalo (eds.): *New Analytical and Geometric Methods in Inverse Problems*, Springer Verlag, 93-126.

- [21] Isozaki, H., Uhlmann, G.: Hyperbolic Geometry and the Dirichlet-to-Neumann map. To appear in *Advances in Math.*
- [22] Kachalov, A.P. Gaussian beams for the Maxwell equations on a manifold. (Russian) *Zap. Nauchn. Sem. POMI* **285** (2002), 58–87.
- [23] Kachalov, A.P. Nonstationary electromagnetic Gaussian beams in a nonhomogeneous anisotropic medium. *Zap. Nauchn. Sem. POMI* **264** (2000), 83–100, 323.
- [24] Kachalov, A., Kurylev, Y. Multidimensional inverse problem with incomplete boundary spectral data. *Comm. Part. Diff. Equations*, **23** (1998), 55–95.
- [25] Katchalov, A., Kurylev, Y., Lassas, M. *Inverse Boundary Spectral Problems*, Chapman Hall/CRC, Pure and Applied Mathematics, 123. (2001), 290 pp.
- [26] Katchalov A., Kurylev Y., Lassas, M. Energy measurements and equivalence of boundary data for inverse problems on non-compact manifolds. In *Geometric Methods in Inverse Problems and PDE Control* Ed. C. Croke, I. Lasiecka, G. Uhlmann, M. Vogelius, IMA volumes in Mathematics and Applications Volume 137 (2003) pp. 183–214.
- [27] Katsuda A., Kurylev Y., Lassas, M. Stability and reconstruction in Gel’fand inverse boundary spectral problem. In: K. Bingham, Y. Kurylev, E. Somersalo (eds.): *New Analytical and Geometric Methods in Inverse Problems*, 309–320, Springer-Verlag, 2003.
- [28] Kenig C., Sjostrand J., Uhlmann G.: The Calderón problem with partial data, preprint arXiv math.AP/0405486.
- [29] Kurylev, Y. Admissible groups of transformations that preserve the boundary spectral data in multidimensional inverse problems. (Russian) *Dokl. Akad. Nauk*, **327** (1992), 322–325; translated in *Soviet Phys. Dokl.* **37** (1993), 544–545.
- [30] Kurylev, Y. A multidimensional Gel’fand–Levitan inverse boundary problem *Diff. Equat. and Math. Phys.* (Birmingham, AL, 1994), 117–131, Int. Press, 1995.
- [31] Kurylev, Y. An inverse boundary problem for the Schrödinger operator with magnetic field. *J. Math. Phys.* **36** (1995), no. 6, 2761–2776.
- [32] Kurylev, Y. Multidimensional Gel’fand inverse problem and boundary distance map, *Inverse Problems Related with Geometry* (ed. H.Soga) (1997), 1–15.
- [33] Kurylev, Y., Lassas, M. Gelfand inverse problem for a quadratic operator pencil. *J. Funct. Anal.* **176** (2000), no. 2, 247–263.
- [34] Kurylev, Y., Lassas, M. Hyperbolic inverse problem with data on a part of the boundary. *Differential Equations and Mathematical Physics (Birmingham, AL, 1999)*, 259–272, AMS/IP Stud. Adv. Math., **16**, Amer. Math. Soc., 2000.
- [35] Kurylev, Y., Lassas, M. Hyperbolic inverse problem and unique continuation of Cauchy data of solutions along the boundary, *Proc. Roy. Soc. Edinburgh, Ser. A*, **132** (2002), no. 4, 931–949.
- [36] Kurylev, Y., Lassas, M., Somersalo E. Reconstruction of a manifold-from electromagnetic boundary measurements, *Contemporary Mathematics*. 333(2002), Inverse Problems: Theory and Applications. Ed. G. Alessandrini, G. Uhlmann, 147–162.
- [37] Kurylev, Y., Lassas, M., Somersalo E. Focusing waves in electromagnetic inverse problems, *Contemporary Mathematics* 348(2004), 11–22, Inverse Problems and Spectral Theory Ed. H. Isozaki.
- [38] Landau, L., Lifshitz, E. *Course of theoretical physics, Vol. 2. The classical theory of fields*. Pergamon Press, 1975. xiv+402 pp.
- [39] Langer, R.E. An inverse problem in differential equations. *Bull. Amer. Math. Soc* **39** (1933), 814–820.
- [40] Lasiecka, I., Triggiani, R. *Control Theory for Partial Differential Equations*. Cambridge Univ. Press, 2000, pp. 645–1067.

- [41] Lassas, M. Inverse boundary spectral problem for non-selfadjoint Maxwell's equations with incomplete data. *Comm. Part. Diff. Equations* **23** (1998), 629–648.
- [42] Lassas, M. The impedance imaging problem as a low-frequency limit. *Inverse Problems* **13** (1997), no. 6, 1503–1518.
- [43] Lassas, M., Taylor, M., Uhlmann, G. The Dirichlet-to-Neumann map for complete Riemannian manifolds with boundary, *Comm. Anal. Geom.* **11** (2003), 207–22.
- [44] Lassas, M., Uhlmann, G. Determining Riemannian manifold from boundary measurements. *Ann. Sci. Ecole Norm. Sup. (4)* **34** (2001), no. 5, 771–787.
- [45] Lee, J., Uhlmann, G. Determining anisotropic real-analytic conductivities by boundary measurements. *Comm. Pure Appl. Math.* **42** (1989), no. 8, 1097–1112.
- [46] Nachman, A. Reconstructions from boundary measurements. *Ann. of Math. (2)* **128** (1988), no. 3, 531–576.
- [47] Nachman, A. Global uniqueness for a two-dimensional inverse boundary value problem. *Ann. of Math. (2)* **143** (1996), no. 1, 71–96.
- [48] Nachman, A., Sylvester, J., Uhlmann, G. An n -dimensional Borg-Levinson theorem. *Comm. Math. Phys.* **115** (1988), no. 4, 595–605.
- [49] Novikov, R., Khenkin, G. The $\bar{\partial}$ -equation in the multidimensional inverse scattering problem. (Russian) *Uspekhi Mat. Nauk* **42** (1987), no. 3, 93–152.
- [50] Ola, P., Päiväranta, L., Somersalo, E. An inverse boundary value problem in electrodynamics. *Duke Math. J.* **70** (1993), no. 3, 617–653.
- [51] Ola, P., Somersalo, E. Electromagnetic inverse problems and generalized Sommerfeld potentials. *SIAM J. Appl. Math.* **56** (1996), no. 4, 1129–1145.
- [52] Paquet, L. Mixed problems for the Maxwell system (French) *Ann. Fac. Sci. Toulouse Math.* (5) **4** (1982), no. 2, 103–141.
- [53] Picard, R. On the low frequency asymptotics in electromagnetic theory. *J. Reine Angew. Math.* **394** (1984), 50–73.
- [54] Romanov, V.G. An inverse problem of electrodynamics, *Dokl. Mathem.*, **66** (2002), no. 2, 200 – 205.
- [55] Russell, D. Controllability and stabilizability theory for linear partial differential equations: recent progress and open questions. *SIAM Rev.* **20** (1978), 639–739.
- [56] Schlichter, L.B. An inverse boundary value problem in electrodynamics. *Physics* **4** (1953), 411–418.
- [57] Schwarz, G. *Hodge decomposition—a method for solving boundary value problems*. Springer-Verlag, 1995. 155 pp.
- [58] Somersalo, E., Isaacson D., Cheney M. A linearized inverse boundary value problem for Maxwell's equations. *J. Comp. Appl. Math.* **42** (1992), 123–136.
- [59] Sylvester, J. An anisotropic inverse boundary value problem. *Comm. Pure Appl. Math.* **43** (1990), no. 2, 201–232
- [60] Sylvester, J. Linearizations of anisotropic inverse problems. In: L. Päiväranta and E. Somersalo (eds.): *Inverse Problems in Mathematical Physics*. Lecture Notes in Physics 422, Springer-Verlag, 1993.
- [61] Sylvester, J., Uhlmann, G. A global uniqueness theorem for an inverse boundary value problem. *Ann. of Math. (2)* **125** (1987), no. 1, 153–169.
- [62] Tataru, D. Unique continuation for solutions to PDEs; between Hörmander's theorem and Holmgren's theorem. *Comm. Part. Diff. Equations* **20** (1995), no. 5-6, 855–884.
- [63] Tataru, D. Unique continuation for operators with partially analytic coefficients. *J. Math. Pures Appl. (9)* **78** (1999), no. 5, 505–521.
- [64] Whitney, H. *Geometric integration theory*. Princeton University Press, 1957.